

# Cisco Wireless Solutions Software Compatibility Matrix

---

**First Published:** 2017-01-02

**Last Modified:** 2023-03-30

## Cisco Wireless Solutions Software Compatibility Matrix

This document lists the software compatibility matrix information for the Cisco wireless devices used in a Cisco centralized and distributed wireless LAN solution and in converged access solutions.



---

**Note** To view the legacy Cisco wireless devices and the compatible Cisco software releases, see <http://www.cisco.com/c/en/us/td/docs/wireless/compatibility/matrix-legacy/compatibility-matrix-legacy.html>

---

## Conventions

See [Cisco Technical Tips Conventions](#) for information about document conventions.

## Cisco Catalyst 9800 Series Wireless Controller Matrix

This section contains the Cisco Catalyst 9800 Series Wireless Controller's compatibility information with Cisco Identity Services Engine, Cisco Prime Infrastructure, Cisco DNA Center platforms and IRCM with the Cisco AireOS Wireless Controller platform.

Table 1: Cisco Catalyst 9800 Series Wireless Controllers Release Compatibility Matrix

Cisco Catalyst 9800 Series Wireless Controllers	Cisco Identity Services Engine (ISE)	Cisco Prime Infrastructure	Cisco AireOS-IRCM Interoperability	Cisco DNA Center
Cisco IOS XE Dublin 17.11.1	3.2	3.10.4 <sup>1</sup>	8.10.185.0	<a href="#">See Cisco DNA Center Compatibility Information</a>
	3.1		8.10.183.0	
	3.0		8.10.182.0	
	2.7		8.10.181.0	
	2.6		8.10.171.0	
	2.4		8.10.162.0	
			8.10.151.0	
			8.10.142.0	
			8.10.130.0	
			8.8.130.0	
Cisco IOS XE Dublin 17.10.1	3.0	3.10.4	8.10.185.0	<a href="#">See Cisco DNA Center Compatibility Information</a>
	2.7	3.10.3 <sup>1</sup>	8.10.183.0	
	2.6		8.10.182.0	
	2.4		8.10.181.0	
			8.10.171.0	
			8.10.162.0	
			8.10.151.0	
			8.10.142.0	
			8.10.130.0	
			8.8.130.0	
		8.5.176.2		
		8.5.182.104		

Cisco Catalyst 9800 Series Wireless Controllers	Cisco Identity Services Engine (ISE)	Cisco Prime Infrastructure	Cisco AireOS-IRCM Interoperability	Cisco DNA Center
Cisco IOS XE Cupertino 17.9.3	3.2	3.10.4	8.10.185.0	<a href="#">See Cisco DNA Center Compatibility Information</a>
	3.1	3.10.3	8.10.183.0	
	3.0	3.10.2 <sup>1</sup>	8.10.182.0	
	2.7		8.10.181.0	
	2.6		8.10.171.0	
	2.4		8.10.162.0	
			8.10.151.0	
			8.10.142.0	
			8.10.130.0	
			8.8.130.0	
Cisco IOS XE Cupertino 17.9.2	3.1	3.10.4	8.10.185.0	<a href="#">See Cisco DNA Center Compatibility Information</a>
	3.0	3.10.3	8.10.183.0	
	2.7	3.10.2 <sup>1</sup>	8.10.182.0	
	2.6		8.10.181.0	
	2.4		8.10.171.0	
			8.10.162.0	
			8.10.151.0	
			8.10.142.0	
			8.10.130.0	
			8.8.130.0	
		8.5.176.2		
		8.5.182.104		

Cisco Catalyst 9800 Series Wireless Controllers	Cisco Identity Services Engine (ISE)	Cisco Prime Infrastructure	Cisco AireOS-IRCM Interoperability	Cisco DNA Center
Cisco IOS XE Cupertino 17.9.1	3.1 3.0 2.7 2.6 2.4	3.10.4 3.10.3 3.10.2 <sup>1</sup>	8.10.185.0 8.10.183.0 8.10.182.0 8.10.181.0 8.10.171.0 8.10.162.0 8.10.151.0 8.10.142.0 8.10.130.0 8.8.130.0 8.5.176.2 8.5.182.104	<a href="#">See Cisco DNA Center Compatibility Information</a>
Cisco IOS XE Cupertino 17.8.1	3.0 2.7 2.6 2.4	3.10.2 3.10.1 <sup>1</sup>	8.10.185.0 8.10.183.0 8.10.182.0 8.10.181.0 8.10.171.0 8.10.162.0 8.10.151.0 8.10.142.0 8.10.130.0 8.8.130.0 8.5.176.2 8.5.182.104	<a href="#">See Cisco DNA Center Compatibility Information</a>

Cisco Catalyst 9800 Series Wireless Controllers	Cisco Identity Services Engine (ISE)	Cisco Prime Infrastructure	Cisco AireOS-IRCM Interoperability	Cisco DNA Center
Cisco IOS XE Cupertino 17.7.1	3.0	3.10.2	8.10.185.0	<a href="#">See Cisco DNA Center Compatibility Information</a>
	2.7	3.10.1 <sup>1</sup>	8.10.183.0	
	2.6		8.10.182.0	
	2.4		8.10.181.0	
			8.10.171.0	
			8.10.162.0	
			8.10.151.0	
			8.10.142.0	
			8.10.130.0	
			8.8.130.0	
			8.5.176.2	
			8.5.182.104	
			8.5.152.103	
		8.5.164.216		
Cisco IOS XE Bengaluru 17.6.5	3.1	3.10.1	8.10.185.0	<a href="#">See Cisco DNA Center Compatibility Information</a>
	3.0	3.10 <sup>1</sup>	8.10.183.0	
	2.7		8.10.182.0	
	2.6		8.10.181.0	
	2.4		8.10.171.0	
			8.10.162.0	
			8.10.151.0	
			8.10.142.0	
			8.10.130.0	
			8.8.130.0	
			8.5.182.104	
			8.5.176.0	
			8.5.176.2	
		8.5.164.0		
		8.5.164.216		

Cisco Catalyst 9800 Series Wireless Controllers	Cisco Identity Services Engine (ISE)	Cisco Prime Infrastructure	Cisco AireOS-IRCM Interoperability	Cisco DNA Center
Cisco IOS XE Bengaluru 17.6.4	3.1	3.10.1	8.10.185.0	<a href="#">See Cisco DNA Center Compatibility Information</a>
	3.0	3.10 <sup>1</sup>	8.10.183.0	
	2.7		8.10.182.0	
	2.6		8.10.181.0	
	2.4		8.10.171.0	
			8.10.162.0	
			8.10.151.0	
			8.10.142.0	
			8.10.130.0	
			8.8.130.0	
			8.5.182.104	
			8.5.176.0	
			8.5.176.2	
			8.5.164.0	
			8.5.164.216	
Cisco IOS XE Bengaluru 17.6.3	3.1	3.10.1	8.10.185.0	<a href="#">See Cisco DNA Center Compatibility Information</a>
	3.0	3.10 <sup>1</sup>	8.10.183.0	
	2.7		8.10.182.0	
	2.6		8.10.181.0	
	2.4		8.10.171.0	
			8.10.162.0	
			8.10.151.0	
			8.10.142.0	
			8.10.130.0	
			8.8.130.0	
			8.5.182.104	
			8.5.176.0	
			8.5.176.2	
			8.5.164.0	
			8.5.164.216	

Cisco Catalyst 9800 Series Wireless Controllers	Cisco Identity Services Engine (ISE)	Cisco Prime Infrastructure	Cisco AireOS-IRCM Interoperability	Cisco DNA Center
Cisco IOS XE Bengaluru 17.6.2	3.1	3.10.1	8.10.185.0	<a href="#">See Cisco DNA Center Compatibility Information</a>
	3.0	3.10 <sup>1</sup>	8.10.183.0	
	2.7		8.10.182.0	
	2.6		8.10.181.0	
	2.4		8.10.171.0	
			8.10.162.0	
			8.10.151.0	
			8.10.142.0	
			8.10.130.0	
			8.8.130.0	
			8.5.164.0	
			8.5.182.104	
			8.5.152.103	
			8.5.164.216	
		8.5.176.2		
Cisco IOS XE Bengaluru 17.6.1	3.1	3.10.1	8.10.185.0	<a href="#">See Cisco DNA Center Compatibility Information</a>
	3.0	3.10 <sup>1</sup>	8.10.183.0	
	2.7		8.10.182.0	
	2.6		8.10.181.0	
	2.4		8.10.171.0	
			8.10.162.0	
			8.5.176.2	
			8.5.182.104	
			8.5.152.103	
			8.5.164.216	

Cisco Catalyst 9800 Series Wireless Controllers	Cisco Identity Services Engine (ISE)	Cisco Prime Infrastructure	Cisco AireOS-IRCM Interoperability	Cisco DNA Center
Cisco IOS XE Bengaluru 17.5.1	3.0 2.7 2.6 2.4	3.10 3.9.1 <sup>1</sup>	8.10.185.0 8.10.183.0 8.10.182.0 8.10.181.0 8.10.171.0 8.10.162.0 8.10.151.0 8.10.142.0 8.10.130.0 8.8.130.0 8.5.164.216 8.5.182.104 8.5.152.103 8.5.164.216 8.5.176.2	<a href="#">See Cisco DNA Center Compatibility Information</a>
Cisco IOS XE Bengaluru 17.4.1	3.0 2.7 2.6 2.4	3.10 3.9.1 3.9 <sup>1</sup>	8.10.185.0 8.10.183.0 8.10.182.0 8.10.181.0 8.10.171.0 8.10.162.0 8.10.151.0 8.10.142.0 8.10.130.0 8.8.130.0 8.5.182.104 8.5.164.216 8.5.176.2 8.5.152.103	<a href="#">See Cisco DNA Center Compatibility Information</a>



Cisco Catalyst 9800 Series Wireless Controllers	Cisco Identity Services Engine (ISE)	Cisco Prime Infrastructure	Cisco AireOS-IRCM Interoperability	Cisco DNA Center
Cisco IOS XE Amsterdam 17.3.6	3.1 3.0 2.7 2.6 2.4	3.10.1 3.9.1 3.9 3.8.1	8.10.185.0 8.10.183.0 8.10.182.0 8.10.181.0 8.10.171.0 8.10.162.0 8.10.160.0 8.10.151.0 8.10.142.0 8.10.130.0 8.8.130.0 8.8.125.0 8.8.120.0 8.8.111.0 8.5.182.104 8.5.176.2 8.5.164.216	<a href="#">See Cisco DNA Center Compatibility Information</a>

Cisco Catalyst 9800 Series Wireless Controllers	Cisco Identity Services Engine (ISE)	Cisco Prime Infrastructure	Cisco AireOS-IRCM Interoperability	Cisco DNA Center
Cisco IOS XE Amsterdam 17.3.5b	3.1	3.10.1	8.10.185.0	See <a href="#">Cisco DNA Center Compatibility Information</a>
	3.0	3.9.1	8.10.183.0	
	2.7	3.9	8.10.182.0	
	2.6	3.8.1 <sup>1</sup>	8.10.181.0	
	2.4		8.10.171.0	
			8.10.162.0	
			8.10.160.0	
			8.10.151.0	
			8.10.142.0	
			8.10.130.0	
			8.8.130.0	
			8.8.125.0	
			8.8.120.0	
			8.8.111.0	
			8.5.182.104	
			8.5.176.0	
			8.5.176.2	
		8.5.164.0		
		8.5.164.216		

Cisco Catalyst 9800 Series Wireless Controllers	Cisco Identity Services Engine (ISE)	Cisco Prime Infrastructure	Cisco AireOS-IRCM Interoperability	Cisco DNA Center
Cisco IOS XE Amsterdam 17.3.5a	3.1	3.10.1	8.10.185.0	See <a href="#">Cisco DNA Center Compatibility Information</a>
	3.0	3.9.1	8.10.183.0	
	2.7	3.9	8.10.182.0	
	2.6	3.8.1 <sup>1</sup>	8.10.181.0	
	2.4		8.10.171.0	
			8.10.162.0	
			8.10.160.0	
			8.10.151.0	
			8.10.142.0	
			8.10.130.0	
			8.8.130.0	
			8.8.125.0	
			8.8.120.0	
			8.8.111.0	
			8.5.182.104	
			8.5.176.0	
		8.5.176.2		
		8.5.164.0		
		8.5.164.216		

Cisco Catalyst 9800 Series Wireless Controllers	Cisco Identity Services Engine (ISE)	Cisco Prime Infrastructure	Cisco AireOS-IRCM Interoperability	Cisco DNA Center
Cisco IOS XE Amsterdam 17.3.4c	3.0	3.9.1	8.10.185.0	See <a href="#">Cisco DNA Center Compatibility Information</a>
	2.7	3.9	8.10.183.0	
	2.6	3.8.1 <sup>1</sup>	8.10.182.0	
	2.4		8.10.181.0	
			8.10.171.0	
			8.10.162.0	
			8.10.160.0	
			8.10.151.0	
			8.10.142.0	
			8.10.130.0	
			8.8.130.0	
			8.8.125.0	
			8.8.120.0	
			8.8.111.0	
		8.5.176.0		
		8.5.164.0		

Cisco Catalyst 9800 Series Wireless Controllers	Cisco Identity Services Engine (ISE)	Cisco Prime Infrastructure	Cisco AireOS-IRCM Interoperability	Cisco DNA Center
Cisco IOS XE Amsterdam 17.3.4	3.0	3.9.1	8.10.185.0	See <a href="#">Cisco DNA Center Compatibility Information</a>
	2.7	3.9	8.10.183.0	
	2.6	3.8.1 <sup>1</sup>	8.10.182.0	
	2.4		8.10.181.0	
			8.10.171.0	
			8.10.162.0	
			8.10.160.0	
			8.10.151.0	
			8.10.142.0	
			8.10.130.0	
			8.8.130.0	
			8.8.125.0	
			8.8.120.0	
			8.8.111.0	
			8.5.176.0	
		8.5.164.0		

Cisco Catalyst 9800 Series Wireless Controllers	Cisco Identity Services Engine (ISE)	Cisco Prime Infrastructure	Cisco AireOS-IRCM Interoperability	Cisco DNA Center
Cisco IOS XE Amsterdam 17.3.3	2.7	3.9.1	8.10.185.0	See <a href="#">Cisco DNA Center Compatibility Information</a>
	2.6	3.9	8.10.183.0	
	2.4	3.8.1 <sup>1</sup>	8.10.182.0	
			8.10.181.0	
			8.10.171.0	
			8.10.162.0	
			8.10.151.0	
			8.10.142.0	
			8.10.130.0	
			8.8.130.0	
			8.8.125.0	
			8.8.120.0	
			8.8.111.0	
			8.5.164.0	
			8.5.182.104	
			8.5.152.103	
		8.5.164.216		
		8.5.176.2		

Cisco Catalyst 9800 Series Wireless Controllers	Cisco Identity Services Engine (ISE)	Cisco Prime Infrastructure	Cisco AireOS-IRCM Interoperability	Cisco DNA Center
Cisco IOS XE Amsterdam 17.3.2a	2.7 2.6 2.4	3.9.1 3.9 3.8.1 <a href="#">Cisco Catalyst 9800 Series Wireless Controller Matrix</a>	8.10.185.0 8.10.183.0 8.10.182.0 8.10.181.0 8.10.171.0 8.10.162.0 8.10.151.0 8.10.142.0 8.10.130.0 8.8.130.0 8.8.125.0 8.8.120.0 8.8.111.0 8.5.164.0 8.5.182.104 8.5.152.103 8.5.164.216 8.5.176.2	<a href="#">See Cisco DNA Center Compatibility Information</a>

Cisco Catalyst 9800 Series Wireless Controllers	Cisco Identity Services Engine (ISE)	Cisco Prime Infrastructure	Cisco AireOS-IRCM Interoperability	Cisco DNA Center
Cisco IOS XE Amsterdam 17.3.1	2.7	3.9.1	8.10.185.0	See <a href="#">Cisco DNA Center Compatibility Information</a>
	2.6	3.9	8.10.183.0	
	2.4	3.8.1 <sup>1</sup>	8.10.182.0	
			8.10.181.0	
			8.10.171.0	
			8.10.162.0	
			8.10.142.0	
			8.10.130.0	
			8.10.122.0	
			8.10.121.0	
			8.10.113.0	
			8.10.112.0	
			8.10.105.0	
			8.9.111.0	
			8.9.100.0	
			8.8.125.0	
			8.8.120.0	
			8.8.111.0	
			8.5.164.0	
			8.5.182.104	
		8.5.152.103		
		8.5.164.216		
		8.5.176.2		



Cisco Catalyst 9800 Series Wireless Controllers	Cisco Identity Services Engine (ISE)	Cisco Prime Infrastructure	Cisco AireOS-IRCM Interoperability	Cisco DNA Center
Cisco IOS XE Amsterdam 17.2.1a	2.7	3.9	8.10.185.0	See <a href="#">Cisco DNA Center Compatibility Information</a>
Cisco IOS XE Amsterdam 17.2.1	2.6	3.8.1	8.10.183.0	
	2.4	3.8 <sup>1</sup>	8.10.182.0	
		8.10.181.0		
		8.10.171.0		
		8.10.162.0		
		8.10.122.0		
		8.10.121.0		
		8.10.113.0		
		8.10.112.0		
		8.10.105.0		
		8.9.111.0		
		8.9.100.0		
		8.8.125.0		
		8.8.120.0		
	8.8.111.0			
	8.5.164.0			

Cisco Catalyst 9800 Series Wireless Controllers	Cisco Identity Services Engine (ISE)	Cisco Prime Infrastructure	Cisco AireOS-IRCM Interoperability	Cisco DNA Center
Cisco IOS XE Gibraltar 17.1.1t	2.7	3.8.1	8.10.185.0	See Cisco DNA Center Compatibility Information
Cisco IOS XE Gibraltar 17.1.1s	2.6	3.8	8.10.183.0	
	2.4	3.7.1	8.10.182.0	
			8.10.181.0	
			8.10.171.0	
			8.10.162.0	
			8.10.113.0	
			8.10.112.0	
			8.10.105.0	
			8.9.111.0	
			8.9.100.0	
			8.8.125.0	
			8.8.120.0	
8.8.111.0				
8.5.164.0				
Cisco IOS XE Gibraltar 16.12.8	2.6	3.7.1	8.10.185.0	See Cisco DNA Center Compatibility Information
2.4	8.10.183.0			
	8.10.182.0			
	8.10.181.0			
	8.10.171.0			
	8.10.162.0			
	8.10.151.0			
	8.10.142.0			
	8.10.130.0			
	8.8.130.0			
	8.8.125.0			
	8.5.176.0			
8.5.164.0				

Cisco Catalyst 9800 Series Wireless Controllers	Cisco Identity Services Engine (ISE)	Cisco Prime Infrastructure	Cisco AireOS-IRCM Interoperability	Cisco DNA Center
Cisco IOS XE Gibraltar 16.12.7	2.6 2.4 2.3	3.7.1	8.10.185.0 8.10.183.0 8.10.182.0 8.10.181.0 8.10.171.0 8.10.162.10 8.10.151.0 8.10.142.0 8.10.130.0 8.8.130.0 8.8.125.0 8.5.176.0 8.5.164.0	<a href="#">See Cisco DNA Center Compatibility Information</a>
Cisco IOS XE Gibraltar 16.12.6a	2.6 2.4 2.3	3.7.1 3.7	8.10.185.0 8.10.183.0 8.10.182.0 8.10.181.0 8.10.171.0 8.10.162.10 8.10.151.0 8.10.142.0 8.10.130.0 8.8.130.0 8.8.125.0 8.5.176.0 8.5.164.0	<a href="#">See Cisco DNA Center Compatibility Information</a>

Cisco Catalyst 9800 Series Wireless Controllers	Cisco Identity Services Engine (ISE)	Cisco Prime Infrastructure	Cisco AireOS-IRCM Interoperability	Cisco DNA Center
Cisco IOS XE Gibraltar 16.12.5	2.6 2.4 2.3	3.7.1 3.7	8.10.185.0 8.10.183.0 8.10.182.0 8.10.181.0 8.10.171.0 8.10.162.0 8.10.151.0 8.10.142.0 8.10.130.0 8.8.130.0 8.8.125.0 8.5.164.0	<a href="#">See Cisco DNA Center Compatibility Information</a>
Cisco IOS XE Gibraltar 16.12.4a	2.6 2.4 2.3 2.2	3.7.1 3.7	8.10.185.0 8.10.183.0 8.10.182.0 8.10.181.0 8.10.171.0 8.10.162.0 8.10.142.0 8.10.130.0 8.10.122.0 8.10.121.0 8.10.113.0 8.10.112.0 8.10.105.0 8.9.111.0 8.9.100.0 8.8.125.0 8.8.120.0 8.8.111.0 8.5.164.0	<a href="#">See Cisco DNA Center Compatibility Information</a>

Cisco Catalyst 9800 Series Wireless Controllers	Cisco Identity Services Engine (ISE)	Cisco Prime Infrastructure	Cisco AireOS-IRCM Interoperability	Cisco DNA Center
Cisco IOS XE Gibraltar 16.12.3	2.6 2.4 2.3 2.2	3.7.1 3.7	8.10.185.0 8.10.183.0 8.10.182.0 8.10.181.0 8.10.171.0 8.10.162.0 8.10.113.0 8.10.112.0 8.10.105.0 8.9.111.0 8.9.100.0 8.8.125.0 8.8.120.0 8.8.111.0 8.5.164.0	<a href="#">See Cisco DNA Center Compatibility Information</a>
Cisco IOS XE Gibraltar 16.12.2s	2.6 2.4 2.3 2.2	3.7.1 3.7	8.10.185.0 8.10.183.0 8.10.182.0 8.10.181.0 8.10.171.0 8.10.162.0 8.9.111.0 8.9.100.0 8.8.125.0 8.8.120.0 8.8.111.0 8.5.164.0	<a href="#">See Cisco DNA Center Compatibility Information</a>

Cisco Catalyst 9800 Series Wireless Controllers	Cisco Identity Services Engine (ISE)	Cisco Prime Infrastructure	Cisco AireOS-IRCM Interoperability	Cisco DNA Center
Cisco IOS XE Gibraltar 16.12.1t	2.6 2.4 2.3 2.2	3.7.1 3.7	8.10.185.0 8.10.183.0 8.10.182.0 8.10.181.0 8.10.171.0 8.10.162.0 8.9.111.0 8.9.100.0 8.8.125.0 8.8.120.0 8.8.111.0 8.5.164.0	<a href="#">See Cisco DNA Center Compatibility Information</a>
Cisco IOS XE Gibraltar 16.12.1s	2.6 2.4 2.3 2.2	3.7.1 3.7	8.10.185.0 8.10.183.0 8.10.182.0 8.10.181.0 8.10.171.0 8.10.162.0 8.9.111.0 8.9.100.0 8.8.125.0 8.8.120.0 8.8.111.0 8.5.164.0	<a href="#">See Cisco DNA Center Compatibility Information</a>

Cisco Catalyst 9800 Series Wireless Controllers	Cisco Identity Services Engine (ISE)	Cisco Prime Infrastructure	Cisco AireOS-IRCM Interoperability	Cisco DNA Center
Cisco IOS XE Gibraltar 16.12.1	2.6 2.4 2.3 2.2	3.7.1 3.7	8.10.185.0 8.10.183.0 8.10.182.0 8.10.181.0 8.10.171.0 8.10.162.0 8.9.111.0 8.9.100.0 8.8.125.0 8.8.120.0 8.8.111.0 8.5.164.0	<a href="#">See Cisco DNA Center Compatibility Information</a>
Cisco IOS XE Gibraltar 16.11.1c	2.6 2.4 2.3 2.2	3.6	8.10.185.0 8.10.183.0 8.10.182.0 8.10.181.0 8.10.171.0 8.10.162.0 8.9.100.0 8.8.111.0 8.5.164.0	<a href="#">See Cisco DNA Center Compatibility Information</a>
Cisco IOS XE Gibraltar 16.11.1b	2.6 2.4 2.3 2.2	3.6	8.10.185.0 8.10.183.0 8.10.182.0 8.10.181.0 8.10.171.0 8.10.162.0 8.9.100.0 8.8.111.0 8.5.164.0	<a href="#">See Cisco DNA Center Compatibility Information</a>

Cisco Catalyst 9800 Series Wireless Controllers	Cisco Identity Services Engine (ISE)	Cisco Prime Infrastructure	Cisco AireOS-IRCM Interoperability	Cisco DNA Center
Cisco IOS XE Gibraltar 16.10.1	2.4	3.5	8.10.185.0	See <a href="#">Cisco DNA Center Compatibility Information</a>
	2.3	3.6	8.10.183.0	
	2.2		8.10.182.0	
			8.10.181.0	
			8.10.171.0	
			8.10.162.0	
			8.8.111.0	
Cisco IOS XE Gibraltar 16.10.1e	2.4	3.5	8.10.185.0	See <a href="#">Cisco DNA Center Compatibility Information</a>
	2.3	3.6	8.10.183.0	
	2.2		8.10.182.0	
			8.10.181.0	
			8.10.171.0	
			8.10.162.0	
			8.8.111.0	
		8.5.164.0		

Base release of Cisco Prime infrastructure that supports corresponding Cisco Catalyst 9800 Series Wireless Controller platform release and its features.



**Note** For Cisco CMX compatibility details, see [Cisco Connected Mobile Experiences Compatibility Matrix](#).



**Note**

- Cisco Prime Infrastructure Release 3.8 does not support Cisco Catalyst 9800 Series Wireless Controllers 16.12.x and 17.1.x releases.
- Cisco Catalyst 9800 Series Wireless Controllers use CAPWAP-based tunnels for mobility. The mobility control channel is encrypted and the mobility data channel can be optionally encrypted. This is termed as Secure Mobility. For more information about IRCM between Cisco IOS XE releases for Cisco Catalyst 9800 Series Wireless Controllers and Cisco Wireless Release for AireOS Controllers, see the [Cisco Catalyst 9800 Wireless Controller-AireOS IRCM Deployment Guide](#).



## Cisco Embedded Wireless Controller Matrix

This section contains the Cisco Embedded Wireless Controller compatibility information with Cisco Identity Services Engine (ISE) and DNA Center platforms.

**Table 2: Cisco Embedded Wireless Controller on Catalyst Access Points Release Compatibility Matrix**

Cisco Embedded Wireless Controller on Catalyst Access Points	Cisco ISE	Cisco DNA Center
Cisco IOS XE Dublin 17.11.1	3.0 2.7 2.6 2.4	<a href="#">See Cisco DNA Center Compatibility Information</a>
Cisco IOS XE Dublin 17.10.1	3.0 2.7 2.6 2.4	<a href="#">See Cisco DNA Center Compatibility Information</a>
Cisco IOS XE Cupertino 17.9.3	3.0 2.7 2.6 2.4	<a href="#">See Cisco DNA Center Compatibility Information</a>
Cisco IOS XE Cupertino 17.9.2	3.0 2.7 2.6 2.4	<a href="#">See Cisco DNA Center Compatibility Information</a>
Cisco IOS XE Cupertino 17.9.1	3.0 2.7 2.6 2.4	<a href="#">See Cisco DNA Center Compatibility Information</a>
Cisco IOS XE Cupertino 17.8.1	3.0 2.7 2.6 2.4	<a href="#">See Cisco DNA Center Compatibility Information</a>

Cisco Embedded Wireless Controller on Catalyst Access Points	Cisco ISE	Cisco DNA Center
Cisco IOS XE Cupertino 17.7.1	3.0 2.7 2.6 2.4	<a href="#">See Cisco DNA Center Compatibility Information</a>
Cisco IOS XE Bengaluru 17.6.5	3.0 2.7 2.6 2.4 2.3	<a href="#">See Cisco DNA Center Compatibility Information</a>
Cisco IOS XE Bengaluru 17.6.4	3.0 2.7 2.6 2.4 2.3	<a href="#">See Cisco DNA Center Compatibility Information</a>
Cisco IOS XE Bengaluru 17.6.3	3.0 2.7 2.6 2.4	<a href="#">See Cisco DNA Center Compatibility Information</a>
Cisco IOS XE Bengaluru 17.6.2	3.0 2.7 2.6 2.4	<a href="#">See Cisco DNA Center Compatibility Information</a>
Cisco IOS XE Bengaluru 17.6.1	3.0 2.7 2.6 2.4	<a href="#">See Cisco DNA Center Compatibility Information</a>
Cisco IOS XE Bengaluru 17.5.1	3.0 2.7 2.6 2.4	<a href="#">See Cisco DNA Center Compatibility Information</a>

Cisco Embedded Wireless Controller on Catalyst Access Points	Cisco ISE	Cisco DNA Center
Cisco IOS XE Bengaluru 17.4.1	3.0 2.7 2.6 2.4	See Cisco DNA Center Compatibility Information
Cisco IOS XE Amsterdam 17.3.6	3.0 2.7 2.6 2.4	See Cisco DNA Center Compatibility Information
Cisco IOS XE Amsterdam 17.3.5b	3.0 2.7 2.6 2.4	See Cisco DNA Center Compatibility Information
Cisco IOS XE Amsterdam 17.3.5a	3.0 2.7 2.6 2.4	See Cisco DNA Center Compatibility Information
Cisco IOS XE Amsterdam 17.3.4c	3.0 2.7 2.6 2.4	See Cisco DNA Center Compatibility Information
Cisco IOS XE Amsterdam 17.3.4	3.0 2.7 2.6 2.4	See Cisco DNA Center Compatibility Information
Cisco IOS XE Amsterdam 17.3.3	2.7	See Cisco DNA Center Compatibility Information
Cisco IOS XE Amsterdam 17.3.2a	2.6	
Cisco IOS XE Amsterdam 17.3.1	2.4	
Cisco IOS XE Amsterdam 17.2.1a	2.7	See Cisco DNA Center Compatibility Information
Cisco IOS XE Amsterdam 17.2.1	2.6	
Cisco IOS XE Gibraltar 17.1.1t	2.4	
Cisco IOS XE Gibraltar 17.1.1s		

Cisco Embedded Wireless Controller on Catalyst Access Points	Cisco ISE	Cisco DNA Center
Cisco IOS XE Gibraltar 16.12.8	2.6	See <a href="#">Cisco DNA Center Compatibility Information</a>
Cisco IOS XE Gibraltar 16.12.7	2.4	
Cisco IOS XE Gibraltar 16.12.6a	2.3	
Cisco IOS XE Gibraltar 16.12.5		
Cisco IOS XE Gibraltar 16.12.4a		
Cisco IOS XE Gibraltar 16.12.3		
Cisco IOS XE Gibraltar 16.12.2s		

Table 3: Wireless Controller Foreign and Anchor Support

Foreign + Anchor	Cisco Catalyst 9800 Wireless Controller for Cloud	Cisco Catalyst 9800-40 Wireless Controller	Cisco Catalyst 9800-80 Wireless Controller	Cisco Catalyst 9800-L Wireless Controller
Cisco 3504 Controller	Y	Y	Y	Y
Cisco 5520 Controller	Y	Y	Y	Y
Cisco 8540 Controller	Y	Y	Y	Y

## Cisco Access Points Supported in Cisco Wireless Controller Platform Software Releases

Information about the list of supported access points by respective wireless platforms is listed as follows:

- Cisco 9800 Wireless Controller Releases: [Supported Access Points in Cisco Catalyst 9800 Series Wireless Controller Software Releases, on page 29](#)
- Catalyst 9800 Embedded Wireless Controller Releases: [Supported Access Points in Cisco Catalyst 9800 Embedded Wireless Controller, on page 43](#)
- Cisco AireOS Wireless Controller Releases: [Supported Access Points in Cisco AireOS Wireless Software Releases, on page 51](#)

For information about the features supported on Wave 2 and Wi-Fi 6 Access Points across Cisco IOS XE and AireOS platforms, see the [Feature Matrix for Wave 2 and 802.11ax \(Wi-Fi 6\) Access Points](#) document.

For information about the compatibility of Cisco Prime Infrastructure with Cisco AireOS Controller software, see the *Compatibility Matrix for Legacy Cisco Wireless Solutions* document at:

[https://www.cisco.com/c/en/us/td/docs/wireless/compatibility/matrix-legacy/compatibility-matrix-legacy.html#prime\\_infrastructure](https://www.cisco.com/c/en/us/td/docs/wireless/compatibility/matrix-legacy/compatibility-matrix-legacy.html#prime_infrastructure)

For information about the compatibility of Cisco Mobility Services Engine with Cisco AireOS Controller software, see the *Compatibility Matrix for Legacy Cisco Wireless Solutions* document at:

[https://www.cisco.com/c/en/us/td/docs/wireless/compatibility/matrix-legacy/compatibility-matrix-legacy.html#mobility\\_services\\_engine](https://www.cisco.com/c/en/us/td/docs/wireless/compatibility/matrix-legacy/compatibility-matrix-legacy.html#mobility_services_engine)

For compatibility information about Cisco AireOS Controller software and Cisco ISE, see the [Cisco ISE Compatibility Information page](#).

## Supported Access Points in Cisco Catalyst 9800 Series Wireless Controller Software Releases

**Table 4: Cisco Catalyst 9800 Wireless Controller and Supported Access Points**

IOS XE Release	Access Point Image Version Number	Access Point Release	Supported Access Points
Cisco IOS XE Dublin 17.11.1	17.11.0.155	15.3(3)JPP	<p>Cisco Catalyst APs: 9166I, 9164I, 9162I, 9136I, 9130 (I/D/E), 9120 (I/E/P), 9117I, 9115 (I/E), 9105 (I/W)</p> <p>Cisco Aironet APs: 1815 (I/W), 1830I, 1840I, 1850 (I/E/P), 3800 (I/E/P), 4800</p> <p>Outdoor and Industrial APs: 1542, 1560</p> <p>Integrated Access Point on Cisco 1100 ISR</p> <p>Cisco Catalyst Industrial Wireless 6300 Heavy Duty S Points, Cisco 6300 Series Embedded Services Access Catalyst Industrial Wireless 9167 (E) Heavy Duty Access</p> <p>Sensors: Cisco Aironet 1800s Active Sensor</p> <p>Pluggable Modules: Wi-Fi 6 Pluggable Module for Industrial</p>
Cisco IOS XE Dublin 17.10.1	17.10.0.181	15.3(3)JPO	<p>Cisco Catalyst APs: 9166I, 9164I, 9162I, 9136I, 9130 (I/D/E), 9120 (I/E/P), 9117, 9115 (I/E), 9105 (I/W)</p> <p>Cisco Aironet APs: 1800I, 1815 (I/W), 1830I, 1840I, 1850 (I/E), 3800 (I/E/P), 4800</p> <p>Outdoor and Industrial APs: 1542, 1560</p> <p>Integrated Access Point on Cisco 1100 ISR</p> <p>Cisco Catalyst Industrial Wireless 6300 Heavy Duty S Points, Cisco 6300 Series Embedded Services Access</p> <p>Sensors: Cisco Aironet 1800s Active Sensor</p> <p>Pluggable Modules: Wi-Fi 6 Pluggable Module for Industrial</p>

IOS XE Release	Access Point Image Version Number	Access Point Release	Supported Access Points
Cisco IOS XE Cupertino 17.9.3	17.9.3.50	15.3(3)JPN2	<p>Cisco Catalyst APs: 9166I, 9164I, 9162I, 9136I, 9130 (I/D/E), 9120 (I/E/P), 9117, 9115 (I/E), 9105 (I/W)</p> <p>Cisco Aironet APs: 1800I, 1815 (I/W), 1830I, 1840I, 1850 (I/E), 3800 (I/E/P), 4800</p> <p>Outdoor and Industrial APs: 1542, 1560</p> <p>Integrated Access Point on Cisco 1100 ISR</p> <p>Cisco Industrial Wireless 3700 Series Access Points</p> <p>Cisco Catalyst Industrial Wireless 6300 Heavy Duty Series Points, Cisco 6300 Series Embedded Services Access Points</p> <p>Sensors: Cisco Aironet 1800s Active Sensor</p> <p>Pluggable Modules: Wi-Fi 6 Pluggable Module for Industrial</p> <p>Support for the following Wave 1 APs are reintroduced from release.</p> <ul style="list-style-type: none"> <li>• Cisco Aironet 1570 Series Access Point</li> <li>• Cisco Aironet 1700 Series Access Point</li> <li>• Cisco Aironet 2700 Series Access Point</li> <li>• Cisco Aironet 3700 Series Access Point</li> </ul> <p><b>Note</b></p> <ul style="list-style-type: none"> <li>• Support for the above mentioned Wave 1 APs will not extend beyond the normal product lifecycle support. Refer to the End of Support bulletin for individual APs.</li> <li>• Feature support is on parity with 17.3.x. Features introduced in 17.4.1 or later are supported on these APs in 17.9.3 release.</li> <li>• You can migrate directly to 17.9.3 from 17.x.y where x=4c or above.</li> </ul>

IOS XE Release	Access Point Image Version Number	Access Point Release	Supported Access Points
Cisco IOS XE Cupertino 17.9.2	17.9.2.52	15.3(3)JPN1	<p>Cisco Catalyst APs: 9166I, 9164I, 9162I, 9136I, 9130 (I/D/E), 9120 (I/E/P), 9117, 9115 (I/E), 9105 (I/W)</p> <p>Cisco Aironet APs: 1800I, 1815 (I/W), 1830I, 1840I, 1852 (I/E), 3800 (I/E/P), 4800</p> <p>Outdoor and Industrial APs: 1542, 1560</p> <p>Integrated Access Point on Cisco 1100 ISR</p> <p>Cisco Industrial Wireless 3700 Series Access Points</p> <p>Cisco Catalyst Industrial Wireless 6300 Heavy Duty Series Access Points, Cisco 6300 Series Embedded Services Access Points</p> <p>Sensors: Cisco Aironet 1800s Active Sensor</p> <p>Pluggable Modules: Wi-Fi 6 Pluggable Module for Industrial</p>
Cisco IOS XE Cupertino 17.9.1	17.9.1.8	15.3(3)JPN	<p>Cisco Catalyst APs: 9166, 9164, 9136, *9130 (I/E), 9120 (P), 9117, 9115, *9105 (I/W)</p> <p>*9130 (I/E): VID 02 or earlier</p> <p>*9120 (I/E): VID 06 or earlier</p> <p>*9105 (I): VID 03 or earlier</p> <p>*9105 (W): VID 01</p> <p>Cisco Aironet APs: 1815, 1830, 1840, 1852, 2800, 3800</p> <p>Outdoor and Industrial APs: 1542, 1560</p> <p>Integrated Access Point on Cisco 1100 ISR</p> <p>Cisco Industrial Wireless 3700 Series Access Points</p> <p>Cisco Catalyst Industrial Wireless 6300 Heavy Duty Series Access Points, Cisco 6300 Series Embedded Services Access Points</p> <p>Sensors: Cisco Aironet 1800s Active Sensor</p> <p>Pluggable Modules: Wi-Fi 6 Pluggable Module for Industrial</p>

IOS XE Release	Access Point Image Version Number	Access Point Release	Supported Access Points
Cisco IOS XE Cupertino 17.8.1	17.8.0.144	15.3(3)JPM	<p>Cisco Catalyst APs: 9136, *9130 (I/E), 9124, *9120 (I/E), 9117, 9115, *9105 (I/W)</p> <p>*9130 (I/E): VID 02 or earlier</p> <p>*9120 (I/E): VID 06 or earlier</p> <p>*9105 (I): VID 03 or earlier</p> <p>*9105 (W): VID 01</p> <p>Cisco Aironet APs: 1815, 1830, 1840, 1852, 2800, 3800, 4800 Series Access Points</p> <p>Outdoor and Industrial APs: 1542, 1560</p> <p>Integrated Access Point on Cisco 1100 ISR</p> <p>Cisco Industrial Wireless 3700 Series Access Points</p> <p>Cisco Catalyst Industrial Wireless 6300 Heavy Duty Series Access Points, Cisco 6300 Series Embedded Services Access Points</p> <p>Sensors: Cisco Aironet 1800s Active Sensor</p> <p>Pluggable Modules: Wi-Fi 6 Pluggable Module for Industrial</p>
Cisco IOS XE Cupertino 17.7.1	17.7.1.11	15.3(3)JPL	<p>Cisco Catalyst APs: 9136, *9130 (I/E), 9124, *9120 (I/E), 9117, 9115, *9105 (I/W)</p> <p>*9130 (I/E): VID 02 or earlier</p> <p>*9120 (I/E): VID 06 or earlier</p> <p>*9105 (I): VID 03 or earlier</p> <p>*9105 (W): VID 01</p> <p>Cisco Aironet APs: 1800 (1815, 1830, 1840, and 1852), 2800, 3800, 4800 Series Access Points</p> <p>Outdoor and Industrial APs: 1542, 1560</p> <p>Integrated Access Point on Cisco 1100 ISR</p> <p>Cisco Industrial Wireless 3700 Series Access Points</p> <p>Cisco Catalyst Industrial Wireless 6300 Heavy Duty Series Access Points, Cisco 6300 Series Embedded Services Access Points</p> <p>Sensors: Cisco Aironet 1800s Active Sensor</p> <p>Pluggable Modules: Wi-Fi 6 Pluggable Module for Industrial</p>



IOS XE Release	Access Point Image Version Number	Access Point Release	Supported Access Points
Cisco IOS XE Bengaluru 17.6.5	17.6.5.22	15.3(3)JPK6	<p>Cisco Catalyst APs: 9130 (I/E), 9124 (I/E/D), 9120 (I/E), 9115, 9105 (I/W)</p> <p>Cisco Aironet APs: 1800 (1815, 1830, 1840, and 1852), 4800 Series Access Points</p> <p>Outdoor and Industrial APs: 1542, 1560</p> <p>Integrated Access Point on Cisco 1100 ISR</p> <p>Cisco Industrial Wireless 3700 Series Access Points</p> <p>Cisco Catalyst Industrial Wireless 6300 Heavy Duty Series Access Points, Cisco 6300 Series Embedded Services Access Points</p> <p>Sensors: Cisco Aironet 1800s Active Sensor</p>
Cisco IOS XE Bengaluru 17.6.4	17.6.4.56	15.3(3)JPK5	<p>Cisco Catalyst APs: 9130 (I/E), 9124 (I/E/D), 9120 (I/E), 9115, 9105 (I/W)</p> <p>Cisco Aironet APs: 1800 (1815, 1830, 1840, and 1852), 4800 Series Access Points</p> <p>Outdoor and Industrial APs: 1542, 1560</p> <p>Integrated Access Point on Cisco 1100 ISR</p> <p>Cisco Industrial Wireless 3700 Series Access Points</p> <p>Cisco Catalyst Industrial Wireless 6300 Heavy Duty Series Access Points, Cisco 6300 Series Embedded Services Access Points</p> <p>Sensors: Cisco Aironet 1800s Active Sensor</p>

IOS XE Release	Access Point Image Version Number	Access Point Release	Supported Access Points
Cisco IOS XE Bengaluru 17.6.3	17.6.3.33	15.3(3)JPK4	<p>Cisco Catalyst APs: *9130 (I/E), 9124 (I/E/D), *9120 (I/E), 9117, 9115, *9105 (I/W)</p> <p>*9130 (I/E): VID 02 or earlier</p> <p>*9120 (I/E): VID 06 or earlier</p> <p>*9105 (I): VID 03 or earlier</p> <p>*9105 (W): VID 01</p> <p>Cisco Aironet APs: 1800 (1815, 1830, 1840, and 1852), 2800, 4800 Series Access Points</p> <p>Outdoor and Industrial APs: 1542, 1560</p> <p>Integrated Access Point on Cisco 1100 ISR</p> <p>Cisco Industrial Wireless 3700 Series Access Points</p> <p>Cisco Catalyst Industrial Wireless 6300 Heavy Duty Series Access Points, Cisco 6300 Series Embedded Services Access Points</p> <p>Sensors: Cisco Aironet 1800s Active Sensor</p>
Cisco IOS XE Bengaluru 17.6.2	17.6.2.43	15.3(3)JPK3	<p>Cisco Catalyst APs: *9130 (I/E), 9124 (I/E/D), *9120 (I/E), 9117, 9115, *9105 (I/W)</p> <p>*9130 (I/E): VID 02 or earlier</p> <p>*9120 (I/E): VID 06 or earlier</p> <p>*9105 (I): VID 03 or earlier</p> <p>*9105 (W): VID 01</p> <p>Cisco Aironet APs: 1800 (1815, 1830, 1840, and 1852), 2800, 4800 Series Access Points</p> <p>Outdoor and Industrial APs: 1542, 1560</p> <p>Integrated Access Point on Cisco 1100 ISR</p> <p>Cisco Industrial Wireless 3700 Series Access Points</p> <p>Cisco Catalyst Industrial Wireless 6300 Heavy Duty Series Access Points, Cisco 6300 Series Embedded Services Access Points</p> <p>Sensors: Cisco Aironet 1800s Active Sensor</p>

IOS XE Release	Access Point Image Version Number	Access Point Release	Supported Access Points
Cisco IOS XE Bengaluru 17.6.1	17.6.1.13	15.3(3)JPK2	<p>Cisco Catalyst APs: *9130 (I/E), 9124 (I/D), *9120 (I/E), 9117, 9115, *9105 (I/W)</p> <p>*9130 (I/E): VID 02 or earlier</p> <p>*9120 (I/E): VID 06 or earlier</p> <p>*9105 (I): VID 03 or earlier</p> <p>*9105 (W): VID 01</p> <p>Cisco Aironet APs: 1800 (1815, 1830, 1840, and 1852), 4800 Series Access Points</p> <p>Outdoor and Industrial APs: 1542, 1560</p> <p>Integrated Access Point on Cisco 1100 ISR</p> <p>Cisco Industrial Wireless 3700 Series Access Points</p> <p>Cisco Catalyst Industrial Wireless 6300 Heavy Duty Series Access Points, Cisco 6300 Series Embedded Services Access Points</p> <p>Sensors: Cisco Aironet 1800s Active Sensor</p>
Cisco IOS XE Bengaluru 17.5.1	17.5.1.12	15.3(3)JPK1	<p>Cisco Catalyst APs: *9130 (I/E), 9124 (I/D), *9120 (I/E), 9117, 9115, *9105 (I/W)</p> <p>*9130 (I/E): VID 02 or earlier</p> <p>*9120 (I/E): VID 06 or earlier</p> <p>*9105 (I): VID 03 or earlier</p> <p>*9105 (W): VID 01</p> <p>Cisco Aironet APs: 1800 (1815, 1830, 1840, and 1852), 4800 Series Access Points</p> <p>Outdoor and Industrial APs: 1542, 1560</p> <p>Integrated Access Point on Cisco 1100 ISR</p> <p>Cisco Industrial Wireless 3700 Series Access Points</p> <p>Cisco Catalyst Industrial Wireless 6300 Heavy Duty Series Access Points, Cisco 6300 Series Embedded Services Access Points</p> <p>Sensors: Cisco Aironet 1800s Active Sensor</p>

IOS XE Release	Access Point Image Version Number	Access Point Release	Supported Access Points
Cisco IOS XE Bengaluru 17.4.1	17.4.1.6	15.3(3)JPK	<p>Cisco Catalyst APs: *9130 (I/E), *9120 (I/E), 9120 (P), 9120 (W), *9105 (I/W)</p> <p>*9130 (I/E): VID 02 or earlier</p> <p>*9120 (I/E): VID 06 or earlier</p> <p>*9105 (I): VID 03 or earlier</p> <p>*9105 (W): VID 01</p> <p>Cisco Aironet APs: 1800 (1815, 1830, 1840, and 1852), 2800, 4800 Series Access Points</p> <p>Outdoor and Industrial APs: 1542, 1560</p> <p>Integrated Access Point on Cisco 1100 ISR</p> <p>Cisco Industrial Wireless, 3700 Series Access Points</p> <p>Cisco Catalyst Industrial Wireless 6300 Heavy Duty Series Access Points, Cisco 6300 Series Embedded Services Access Points</p> <p>Sensors: Cisco Aironet 1800s Active Sensor</p>
Cisco IOS XE Amsterdam 17.3.7	17.3.7.36	15.3(3)JPJ10	<p>Cisco Catalyst APs: 9130 (I/E), 9124 (I/E/D), 9120 (I/E), 9117, 9115, 9105 (I/W)</p> <p>Cisco Aironet APs: 1700, 1800 (1810 OEAP, 1815, 1830, 1852), 2700, 2800, 3700, 3800, 4800 Series Access Points</p> <p>Cisco 6300 Series Embedded Services Access Point</p> <p>Cisco Industrial Wireless 3700 Series Access Points</p> <p>Cisco Catalyst Industrial Wireless 6300 Heavy Duty Series Access Points</p> <p>Outdoor and Industrial APs: 1542, 1560, 1570</p> <p>Sensors: Cisco Aironet 1800s Active Sensor</p> <p>Integrated Access Point on Cisco 1100 ISR</p>

IOS XE Release	Access Point Image Version Number	Access Point Release	Supported Access Points
Cisco IOS XE Amsterdam 17.3.6	17.3.6.76	15.3(3)JPJ9	<p>Cisco Catalyst APs: 9130 (I/E), 9124 (I/E/D), 9120 (I/E), 9117, 9115, 9105 (I/W)</p> <p>Cisco Aironet APs: 1700, 1800 (1810 OEAP, 1815, 1852), 2700, 2800, 3700, 3800, 4800 Series Access Points</p> <p>Cisco 6300 Series Embedded Services Access Point</p> <p>Cisco Industrial Wireless 3700 Series Access Points</p> <p>Cisco Catalyst Industrial Wireless 6300 Heavy Duty Series Access Points</p> <p>Outdoor and Industrial APs: 1542, 1560, 1570</p> <p>Sensors: Cisco Aironet 1800s Active Sensor</p> <p>Integrated Access Point on Cisco 1100 ISR</p>
Cisco IOS XE Amsterdam 17.3.5b	17.3.5.43	15.3(3)JPJ8b	<p>Cisco Catalyst APs: *9130 (I/E), 9124 (I/E/D), *9120 (I/E), 9117, 9115, *9105 (I/W)</p> <p>*9130 (I/E): VID 02 or earlier</p> <p>*9120 (I/E): VID 06 or earlier</p> <p>*9105 (I): VID 03 or earlier</p> <p>*9105 (W): VID 01</p> <p>Cisco Aironet APs: 1700, 1800 (1810 OEAP, 1815, 1852), 2700, 2800, 3700, 3800, 4800 Series Access Points</p> <p>Cisco 6300 Series Embedded Services Access Point</p> <p>Cisco Industrial Wireless 3700 Series Access Points</p> <p>Cisco Catalyst Industrial Wireless 6300 Heavy Duty Series Access Points</p> <p>Outdoor and Industrial APs: 1542, 1560, 1570</p> <p>Sensors: Cisco Aironet 1800s Active Sensor</p> <p>Integrated Access Point on Cisco 1100 ISR</p>

IOS XE Release	Access Point Image Version Number	Access Point Release	Supported Access Points
Cisco IOS XE Amsterdam 17.3.5a	17.3.5.42	15.3(3)JPJ8a	<p>Cisco Catalyst APs: *9130 (I/E), 9124 (I/E/D), *9120 (I/E), 9117, 9115, *9105 (I/W)</p> <p>*9130 (I/E): VID 02 or earlier</p> <p>*9120 (I/E): VID 06 or earlier</p> <p>*9105 (I): VID 03 or earlier</p> <p>*9105 (W): VID 01</p> <p>Cisco Aironet APs: 1700, 1800 (1810 OEAP, 1815, 1830, 1852), 2700, 2800, 3700, 3800, 4800 Series Access Points</p> <p>Cisco 6300 Series Embedded Services Access Point</p> <p>Cisco Industrial Wireless 3700 Series Access Points</p> <p>Cisco Catalyst Industrial Wireless 6300 Heavy Duty Series Access Points</p> <p>Outdoor and Industrial APs: 1542, 1560, 1570</p> <p>Sensors: Cisco Aironet 1800s Active Sensor</p> <p>Integrated Access Point on Cisco 1100 ISR</p>
Cisco IOS XE Amsterdam 17.3.4c	17.3.4.40	15.3(3)JPJ7c	<p>Cisco Catalyst APs: *9130 (I/E), 9124 (I/D), *9120 (I/E), 9117, 9115, *9105 (I/W)</p> <p>*9130 (I/E): VID 02 or earlier</p> <p>*9120 (I/E): VID 06 or earlier</p> <p>*9105 (I): VID 03 or earlier</p> <p>*9105 (W): VID 01</p> <p>Cisco Aironet APs: 1700, 1800 (1810 OEAP, 1815, 1830, 1852), 2700, 2800, 3700, 3800, 4800 Series Access Points</p> <p>Cisco 6300 Series Embedded Services Access Point</p> <p>Cisco Industrial Wireless 3700 Series Access Points</p> <p>Cisco Catalyst Industrial Wireless 6300 Heavy Duty Series Access Points</p> <p>Outdoor and Industrial APs: 1542, 1560, 1570</p> <p>Sensors: Cisco Aironet 1800s Active Sensor</p> <p>Integrated Access Point on Cisco 1100 ISR</p>

IOS XE Release	Access Point Image Version Number	Access Point Release	Supported Access Points
Cisco IOS XE Amsterdam 17.3.4	17.3.4.30	15.3(3)JPJ7	<p>Cisco Catalyst APs: *9130 (I/E), 9124 (I/D in B Domain), 9120 (P), 9117, 9115, *9105 (I/W)</p> <p>*9130 (I/E): VID 02 or earlier</p> <p>*9120 (I/E): VID 06 or earlier</p> <p>*9105 (I): VID 03 or earlier</p> <p>*9105 (W): VID 01</p> <p>Cisco Aironet APs: 1700, 1800 (1810 OEAP, 1815, 1852), 2700, 2800, 3700, 3800, 4800 Series Access Points</p> <p>Cisco 6300 Series Embedded Services Access Point</p> <p>Cisco Industrial Wireless 3700 Series Access Points</p> <p>Cisco Catalyst Industrial Wireless 6300 Heavy Duty Series Access Points</p> <p>Outdoor and Industrial APs: 1542, 1560, 1570</p> <p>Sensors: Cisco Aironet 1800s Active Sensor</p> <p>Integrated Access Point on Cisco 1100 ISR</p>
Cisco IOS XE Amsterdam 17.3.3	17.3.3.26	15.3(3)JPJ6	<p>Cisco Catalyst APs: *9130 (I/E), *9120 (I/E), 9120 (P), *9105 (I/W)</p>
Cisco IOS XE Amsterdam 17.3.2a	17.3.2.32	15.3(3)JPJ5	<p>*9130 (I/E): VID 02 or earlier</p> <p>*9120 (I/E): VID 06 or earlier</p>
Cisco IOS XE Amsterdam 17.3.1	17.3.1.9	15.3(3)JPJ4	<p>*9105 (I): VID 03 or earlier</p> <p>*9105 (W): VID 01</p> <p>Cisco Aironet APs: 1700, 1800 (1810 OEAP, 1815, 1852), 2700, 2800, 3700, 3800, 4800 Series Access Points</p> <p>Cisco 6300 Series Embedded Services Access Point</p> <p>Cisco Industrial Wireless 3700 Series Access Points</p> <p>Cisco Catalyst Industrial Wireless 6300 Heavy Duty Series Access Points</p> <p>Outdoor and Industrial APs: 1542, 1560, 1570</p> <p>Sensors: Cisco Aironet 1800s Active Sensor</p> <p>Integrated Access Point on Cisco 1100 ISR</p>

IOS XE Release	Access Point Image Version Number	Access Point Release	Supported Access Points
Cisco IOS XE Amsterdam 17.2.1a	17.2.1.15	15.3(3)JPJ3a	Cisco Catalyst APs: *9130 (I/E), *9120 (I/E), 9120 (P), 9120 (W), *9105 (I/W)
Cisco IOS XE Amsterdam 17.2.1	17.2.1.11	15.3(3)JPJ3	*9130 (I/E): VID 02 or earlier *9120 (I/E): VID 06 or earlier
Cisco IOS XE Gibraltar 17.1.1t	17.1.1.32	15.3(3)JPJ2t	*9105 (I): VID 03 or earlier *9105 (W): VID 01
Cisco IOS XE Gibraltar 17.1.1s	17.1.1.29	15.3(3)JPJ2	Cisco Aironet APs: 9130, 9120, 9117, 9115, 1700, 1800, 1840, 2800, 2800, 3700, 3800, 4800 Series Access Points Cisco 6300 Series Embedded Services Access Point Cisco Industrial Wireless 3700 Series Access Points Cisco Catalyst Industrial Wireless 6300 Heavy Duty Series Access Points Outdoor and Industrial APs: 1542, 1560, 1570 Sensors: Cisco Aironet 1800s Active Sensor Integrated Access Point on Cisco 1100 ISR
Cisco IOS XE Gibraltar 16.12.8	16.12.8.5	15.3(3)JPI10	Cisco Catalyst APs: *9130 (I/E), *9120 (I/E), 9120 (P), 9120 (W), *9105 (I/W) *9130 (I/E): VID 02 or earlier *9120 (I/E): VID 06 or earlier Cisco Aironet APs: 1700, 1800, 1840, 2700, 2800, 3700, 3800, 4800 Series Access Points Cisco Industrial Wireless 3700 Series Access Points Outdoor and Industrial APs: 1542, 1560, 1570 Sensors: Cisco Aironet 1800s Active Sensor Integrated Access Point on Cisco 1100 ISR



IOS XE Release	Access Point Image Version Number	Access Point Release	Supported Access Points
Cisco IOS XE Gibraltar 16.12.7	16.12.7.2	15.3(3)JPI9	<p>Cisco Catalyst APs: *9130 (I/E), *9120 (I/E), 9120 (P)</p> <p>*9130 (I/E): VID 02 or earlier</p> <p>*9120 (I/E): VID 06 or earlier</p> <p>Cisco Aironet APs: 1700, 1800, 1840, 2700, 2800, 3700 Series Access Points</p> <p>Cisco Industrial Wireless 3700 Series Access Points</p> <p>Outdoor and Industrial APs: 1542, 1560, 1570</p> <p>Sensors: Cisco Aironet 1800s Active Sensor</p> <p>Integrated Access Point on Cisco 1100 ISR</p>
Cisco IOS XE Gibraltar 16.12.6a	16.12.6.7	15.3(3)JPI8a	<p>Cisco Catalyst APs: *9130 (I/E), *9120 (I/E), 9120 (P)</p> <p>*9130 (I/E): VID 02 or earlier</p> <p>*9120 (I/E): VID 06 or earlier</p> <p>Cisco Aironet APs: 1700, 1800, 1840, 2700, 2800, 3700 Series Access Points</p> <p>Cisco Industrial Wireless 3700 Series Access Points</p> <p>Outdoor and Industrial APs: 1542, 1560, 1570</p> <p>Sensors: Cisco Aironet 1800s Active Sensor</p> <p>Integrated Access Point on Cisco 1100 ISR</p>
Cisco IOS XE Gibraltar 16.12.5	16.12.5.13	15.3(3)JPI7	<p>Cisco Catalyst APs: *9130 (I/E), *9120 (I/E), 9120 (P)</p> <p>*9130 (I/E): VID 02 or earlier</p>
Cisco IOS XE Gibraltar 16.12.4a	16.12.4.31	15.3(3)JPI6a	<p>*9120 (I/E): VID 06 or earlier</p> <p>Cisco Aironet APs: 1700, 1800, 1840, 2700, 2800, 3700 Series Access Points</p>
Cisco IOS XE Gibraltar 16.12.3	16.12.3.13	15.3(3)JPI5	<p>Cisco Industrial Wireless 3700 Series Access Points</p> <p>Outdoor and Industrial APs: 1542, 1560, 1570</p> <p>Sensors: Cisco Aironet 1800s Active Sensor</p> <p>Integrated Access Point on Cisco 1100 ISR</p>

IOS XE Release	Access Point Image Version Number	Access Point Release	Supported Access Points
Cisco IOS XE Gibraltar 16.12.2s	16.12.2.132	15.3(3)JPI4	<p>Cisco Catalyst APs: *9130 (I/E), *9120 (I/E), 9120 (P), 9115 (P)</p> <p>*9130 (I/E): VID 02 or earlier</p> <p>*9120 (I/E): VID 06 or earlier</p> <p>Cisco Aironet APs: 1700, 1800, 1840, 2700, 2800, 3700, 4700, 5700, 6700, 8700, 9800 Series Access Points</p> <p>Cisco Industrial Wireless 3700 Series Access Points</p> <p>Outdoor and Industrial APs: 1542, 1560, 1570</p> <p>Sensors: Cisco Aironet 1800s Active Sensor</p> <p>Integrated Access Point on Cisco 1100 ISR</p>
Cisco IOS XE Gibraltar 16.12.1t	16.12.1.140	15.3(3)JPI1t	<p>Cisco Catalyst APs: *9120 (I/E), 9120 (P), 9117, 9115</p> <p>*9120 (I/E): VID 06 or earlier</p>
Cisco IOS XE Gibraltar 16.12.1s	16.12.1.139	Not Supported	<p>Cisco Aironet APs: 1700, 1800, 1840, 2700, 2800, 3700, 4700, 5700, 6700, 8700, 9800 Series Access Points</p>
Cisco IOS XE Gibraltar 16.12.1	16.12.0.42	15.3(3)JPI1	<p>Cisco Industrial Wireless 3700 Series Access Points</p> <p>Outdoor and Industrial APs: 1542, 1560, 1570</p> <p>Sensors: Cisco Aironet 1800s Active Sensor</p> <p>Integrated Access Point on Cisco 1100 ISR</p>
Cisco IOS XE Gibraltar 16.11.1c	16.11.1.134	15.3(3)JPH3	<p>Cisco Catalyst APs: *9120 (I/E), 9120 (P), 9117, 9115</p> <p>*9120 (I/E): VID 06 or earlier</p> <p>Cisco Aironet APs: 1700, 1800, 2700, 2800, 3700, 3800, 4700, 5700, 6700, 8700, 9800 Series Access Points</p> <p>Cisco Industrial Wireless 3700 Series Access Points</p> <p>Outdoor and Industrial APs: 1542, 1560, 1570</p> <p>Sensors: Cisco Aironet 1800s Active Sensor</p> <p>Integrated Access Point on Cisco 1100 ISR</p>

IOS XE Release	Access Point Image Version Number	Access Point Release	Supported Access Points
Cisco IOS XE Gibraltar 16.11.1b	16.11.1.133	15.3(3)JPH2	<p>Cisco Catalyst APs: *9120 (I/E), 9120 (P), 9117, 9115</p> <p>*9120 (I/E): VID 06 or earlier</p> <p>Cisco Aironet APs: 1700, 1800, 2700, 2800, 3700, 3800 Access Points</p> <p>Cisco Industrial Wireless 3700 Series Access Points</p> <p>Outdoor and Industrial APs: 1542, 1560, 1570</p> <p>Sensors: Cisco Aironet 1800s Active Sensor</p> <p>Integrated Access Point on Cisco 1100 ISR</p>
Cisco IOS XE Gibraltar 16.10.1e	16.10.1.48	15.3(3)JPG2	<p>Cisco Aironet APs: 1700, 1800, 2700, 2800, 3700, 3800 Access Points</p> <p>Outdoor and Industrial APs: 1542, 1560, 1570</p> <p>Sensors: Cisco Aironet 1800s Active Sensor</p> <p>Integrated Access Point on Cisco 1100 ISR</p>
Cisco IOS XE Gibraltar 16.10.1	16.10.1.42	15.3(3)JI1	<p>Cisco Aironet APs: 1700, 1800, 2700, 2800, 3700, 3800 Access Points</p> <p>Outdoor and Industrial APs: 1542, 1560, 1570</p> <p>Sensors: Cisco Aironet 1800s Active Sensor</p>

## Supported Access Points in Cisco Catalyst 9800 Embedded Wireless Controller

Table 5: Cisco Embedded Wireless Controller and Supported Access Points

IOS XE Releases	Access Point Image Version Number	Access Point Release	Supported Access Points
Cisco IOS XE Dublin 17.11.1	17.11.0.155	15.3(3)JPP	<p>Cisco Catalyst APs: 9130 (I/E), 9124 (I/E), 9117, 9115 (I/E), 9105 (I/W)</p> <p>Cisco Aironet APs: 1800I, 1815 (I/W), 2800 (I/E), 3800 (I/E/P), 4800</p> <p>Cisco Catalyst Industrial Wireless 6300 Series Access Points</p> <p><b>Note</b> 9166I, 9164I, 9162I, 9136I, 9136E, 9136W, 9136X, 9136Y, 9136Z, 9136AA, 9136AB, 9136AC, 9136AD, 9136AE, 9136AF, 9136AG, 9136AH, 9136AI, 9136AJ, 9136AK, 9136AL, 9136AM, 9136AN, 9136AO, 9136AP, 9136AQ, 9136AR, 9136AS, 9136AT, 9136AU, 9136AV, 9136AW, 9136AX, 9136AY, 9136AZ, 9136BA, 9136BB, 9136BC, 9136BD, 9136BE, 9136BF, 9136BG, 9136BH, 9136BI, 9136BJ, 9136BK, 9136BL, 9136BM, 9136BN, 9136BO, 9136BP, 9136BQ, 9136BR, 9136BS, 9136BT, 9136BU, 9136BV, 9136BW, 9136BX, 9136BY, 9136BZ, 9136CA, 9136CB, 9136CC, 9136CD, 9136CE, 9136CF, 9136CG, 9136CH, 9136CI, 9136CJ, 9136CK, 9136CL, 9136CM, 9136CN, 9136CO, 9136CP, 9136CQ, 9136CR, 9136CS, 9136CT, 9136CU, 9136CV, 9136CW, 9136CX, 9136CY, 9136CZ, 9136DA, 9136DB, 9136DC, 9136DD, 9136DE, 9136DF, 9136DG, 9136DH, 9136DI, 9136DJ, 9136DK, 9136DL, 9136DM, 9136DN, 9136DO, 9136DP, 9136DQ, 9136DR, 9136DS, 9136DT, 9136DU, 9136DV, 9136DW, 9136DX, 9136DY, 9136DZ, 9136EA, 9136EB, 9136EC, 9136ED, 9136EE, 9136EF, 9136EG, 9136EH, 9136EI, 9136EJ, 9136EK, 9136EL, 9136EM, 9136EN, 9136EO, 9136EP, 9136EQ, 9136ER, 9136ES, 9136ET, 9136EU, 9136EV, 9136EW, 9136EX, 9136EY, 9136EZ, 9136FA, 9136FB, 9136FC, 9136FD, 9136FE, 9136FF, 9136FG, 9136FH, 9136FI, 9136FJ, 9136FK, 9136FL, 9136FM, 9136FN, 9136FO, 9136FP, 9136FQ, 9136FR, 9136FS, 9136FT, 9136FU, 9136FV, 9136FW, 9136FX, 9136FY, 9136FZ, 9136GA, 9136GB, 9136GC, 9136GD, 9136GE, 9136GF, 9136GG, 9136GH, 9136GI, 9136GJ, 9136GK, 9136GL, 9136GM, 9136GN, 9136GO, 9136GP, 9136GQ, 9136GR, 9136GS, 9136GT, 9136GU, 9136GV, 9136GW, 9136GX, 9136GY, 9136GZ, 9136HA, 9136HB, 9136HC, 9136HD, 9136HE, 9136HF, 9136HG, 9136HH, 9136HI, 9136HJ, 9136HK, 9136HL, 9136HM, 9136HN, 9136HO, 9136HP, 9136HQ, 9136HR, 9136HS, 9136HT, 9136HU, 9136HV, 9136HW, 9136HX, 9136HY, 9136HZ, 9136IA, 9136IB, 9136IC, 9136ID, 9136IE, 9136IF, 9136IG, 9136IH, 9136II, 9136IJ, 9136IK, 9136IL, 9136IM, 9136IN, 9136IO, 9136IP, 9136IQ, 9136IR, 9136IS, 9136IT, 9136IU, 9136IV, 9136IW, 9136IX, 9136IY, 9136IZ, 9136JA, 9136JB, 9136JC, 9136JD, 9136JE, 9136JF, 9136JG, 9136JH, 9136JI, 9136JJ, 9136JK, 9136JL, 9136JM, 9136JN, 9136JO, 9136JP, 9136JQ, 9136JR, 9136JS, 9136JT, 9136JU, 9136JV, 9136JW, 9136JX, 9136JY, 9136JZ, 9136KA, 9136KB, 9136KC, 9136KD, 9136KE, 9136KF, 9136KG, 9136KH, 9136KI, 9136KJ, 9136KK, 9136KL, 9136KM, 9136KN, 9136KO, 9136KP, 9136KQ, 9136KR, 9136KS, 9136KT, 9136KU, 9136KV, 9136KW, 9136KX, 9136KY, 9136KZ, 9136LA, 9136LB, 9136LC, 9136LD, 9136LE, 9136LF, 9136LG, 9136LH, 9136LI, 9136LJ, 9136LK, 9136LL, 9136LM, 9136LN, 9136LO, 9136LP, 9136LQ, 9136LR, 9136LS, 9136LT, 9136LU, 9136LV, 9136LW, 9136LX, 9136LY, 9136LZ, 9136MA, 9136MB, 9136MC, 9136MD, 9136ME, 9136MF, 9136MG, 9136MH, 9136MI, 9136MJ, 9136MK, 9136ML, 9136MM, 9136MN, 9136MO, 9136MP, 9136MQ, 9136MR, 9136MS, 9136MT, 9136MU, 9136MV, 9136MW, 9136MX, 9136MY, 9136MZ, 9136NA, 9136NB, 9136NC, 9136ND, 9136NE, 9136NF, 9136NG, 9136NH, 9136NI, 9136NJ, 9136NK, 9136NL, 9136NM, 9136NN, 9136NO, 9136NP, 9136NQ, 9136NR, 9136NS, 9136NT, 9136NU, 9136NV, 9136NW, 9136NX, 9136NY, 9136NZ, 9136OA, 9136OB, 9136OC, 9136OD, 9136OE, 9136OF, 9136OG, 9136OH, 9136OI, 9136OJ, 9136OK, 9136OL, 9136OM, 9136ON, 9136OO, 9136OP, 9136OQ, 9136OR, 9136OS, 9136OT, 9136OU, 9136OV, 9136OW, 9136OX, 9136OY, 9136OZ, 9136PA, 9136PB, 9136PC, 9136PD, 9136PE, 9136PF, 9136PG, 9136PH, 9136PI, 9136PJ, 9136PK, 9136PL, 9136PM, 9136PN, 9136PO, 9136PP, 9136PQ, 9136PR, 9136PS, 9136PT, 9136PU, 9136PV, 9136PW, 9136PX, 9136PY, 9136PZ, 9136QA, 9136QB, 9136QC, 9136QD, 9136QE, 9136QF, 9136QG, 9136QH, 9136QI, 9136QJ, 9136QK, 9136QL, 9136QM, 9136QN, 9136QO, 9136QP, 9136QQ, 9136QR, 9136QS, 9136QT, 9136QU, 9136QV, 9136QW, 9136QX, 9136QY, 9136QZ, 9136RA, 9136RB, 9136RC, 9136RD, 9136RE, 9136RF, 9136RG, 9136RH, 9136RI, 9136RJ, 9136RK, 9136RL, 9136RM, 9136RN, 9136RO, 9136RP, 9136RQ, 9136RR, 9136RS, 9136RT, 9136RU, 9136RV, 9136RW, 9136RX, 9136RY, 9136RZ, 9136SA, 9136SB, 9136SC, 9136SD, 9136SE, 9136SF, 9136SG, 9136SH, 9136SI, 9136SJ, 9136SK, 9136SL, 9136SM, 9136SN, 9136SO, 9136SP, 9136SQ, 9136SR, 9136SS, 9136ST, 9136SU, 9136SV, 9136SW, 9136SX, 9136SY, 9136SZ, 9136TA, 9136TB, 9136TC, 9136TD, 9136TE, 9136TF, 9136TG, 9136TH, 9136TI, 9136TJ, 9136TK, 9136TL, 9136TM, 9136TN, 9136TO, 9136TP, 9136TQ, 9136TR, 9136TS, 9136TT, 9136TU, 9136TV, 9136TW, 9136TX, 9136TY, 9136TZ, 9136UA, 9136UB, 9136UC, 9136UD, 9136UE, 9136UF, 9136UG, 9136UH, 9136UI, 9136UJ, 9136UK, 9136UL, 9136UM, 9136UN, 9136UO, 9136UP, 9136UQ, 9136UR, 9136US, 9136UT, 9136UU, 9136UV, 9136UW, 9136UX, 9136UY, 9136UZ, 9136VA, 9136VB, 9136VC, 9136VD, 9136VE, 9136VF, 9136VG, 9136VH, 9136VI, 9136VJ, 9136VK, 9136VL, 9136VM, 9136VN, 9136VO, 9136VP, 9136VQ, 9136VR, 9136VS, 9136VT, 9136VU, 9136VV, 9136VW, 9136VX, 9136VY, 9136VZ, 9136WA, 9136WB, 9136WC, 9136WD, 9136WE, 9136WF, 9136WG, 9136WH, 9136WI, 9136WJ, 9136WK, 9136WL, 9136WM, 9136WN, 9136WO, 9136WP, 9136WQ, 9136WR, 9136WS, 9136WT, 9136WU, 9136WV, 9136WW, 9136WX, 9136WY, 9136WZ, 9136XA, 9136XB, 9136XC, 9136XD, 9136XE, 9136XF, 9136XG, 9136XH, 9136XI, 9136XJ, 9136XK, 9136XL, 9136XM, 9136XN, 9136XO, 9136XP, 9136XQ, 9136XR, 9136XS, 9136XT, 9136XU, 9136XV, 9136XW, 9136XX, 9136XY, 9136XZ, 9136YA, 9136YB, 9136YC, 9136YD, 9136YE, 9136YF, 9136YG, 9136YH, 9136YI, 9136YJ, 9136YK, 9136YL, 9136YM, 9136YN, 9136YO, 9136YP, 9136YQ, 9136YR, 9136YS, 9136YT, 9136YU, 9136YV, 9136YW, 9136YX, 9136YY, 9136YZ, 9136ZA, 9136ZB, 9136ZC, 9136ZD, 9136ZE, 9136ZF, 9136ZG, 9136ZH, 9136ZI, 9136ZJ, 9136ZK, 9136ZL, 9136ZM, 9136ZN, 9136ZO, 9136ZP, 9136ZQ, 9136ZR, 9136ZS, 9136ZT, 9136ZU, 9136ZV, 9136ZW, 9136ZX, 9136ZY, 9136ZZ</p>

IOS XE Releases	Access Point Image Version Number	Access Point Release	Supported Access Points
Cisco IOS XE Dublin 17.10.1	17.10.0.181	15.3(3)JPO	<p>Cisco Catalyst APs: 9130 (I/E), 9124 (I/D), 9117, 9115 (I/E), 9105 (I/W)</p> <p>Cisco Aironet APs: 1800I, 1815 (I/W), 1850, 2800 (I/E), 3800 (I/E/P), 4800</p> <p>Cisco Catalyst Industrial Wireless 6300 H Series Access Points</p> <p><b>Note</b> 9166I, 9164I, 9162I, 9136I on Catalyst 9k switches with Embedded Wireless Controller in SDA mode.</p>
Cisco IOS XE Cupertino 17.9.3	17.9.3.50	15.3(3)JPN2	<p>Cisco Catalyst APs: 9130 (I/E), 9124 (I/D), 9117, 9115 (I/E), 9105 (I/W)</p> <p>Cisco Aironet APs: 1815, 1830, 1840, 1850, 4800</p> <p>Cisco Catalyst Industrial Wireless 6300 H Series Access Points</p> <p><b>Note</b> 9166I, 9164I, 9162I, 9136I on Catalyst 9k switches with Embedded Wireless Controller in SDA mode.</p>
Cisco IOS XE Cupertino 17.9.2	17.9.2.52	15.3(3)JPN1	<p>Cisco Catalyst APs: 9130 (I/E), 9124 (I/D), 9117, 9115 (I/E), 9105 (I/W)</p> <p>Cisco Aironet APs: 1815, 1830, 1840, 1850, 4800</p> <p>Cisco Catalyst Industrial Wireless 6300 H Series Access Points</p> <p><b>Note</b> 9166I, 9164I, 9162I, 9136I on Catalyst 9k switches with Embedded Wireless Controller in SDA mode.</p>

IOS XE Releases	Access Point Image Version Number	Access Point Release	Supported Access Points
Cisco IOS XE Cupertino 17.9.1	17.9.1.8	15.3(3)JPN	<p>Cisco Catalyst APs: *9130 (I/E), 9124, 9120 (P), 9117, 9115 (I/E), *9105 (I/W)</p> <p>*9130 (I/E): VID 02 or earlier</p> <p>*9120 (I/E): VID 06 or earlier</p> <p>*9105 (I): VID 03 or earlier</p> <p>*9105 (W): VID 01</p> <p>Cisco Aironet APs: 1815, 1830, 1840, 4800</p> <p>Cisco Catalyst Industrial Wireless 6300 Access Points</p> <p><b>Note</b> 9166I, 9164I, 9136I only with Cisco Catalyst 9k switches with Embedded Wireless Controller in SDA mode.</p>
Cisco IOS XE Cupertino 17.8.1	17.8.0.144	15.3(3)JPM	<p>Cisco Catalyst APs: *9130 (I/E), 9124, 9120 (P), 9117, 9115 (I/E), *9105 (I/W)</p> <p>*9130 (I/E): VID 02 or earlier</p> <p>*9120 (I/E): VID 06 or earlier</p> <p>*9105 (I): VID 03 or earlier</p> <p>*9105 (W): VID 01</p> <p>Cisco Aironet APs: 1815, 1830, 1840, 4800</p> <p>Cisco Catalyst Industrial Wireless 6300 Access Points</p> <p><b>Note</b> 9136I only with Cisco Catalyst 9k switches with Embedded Wireless Controller in SDA mode.</p>

IOS XE Releases	Access Point Image Version Number	Access Point Release	Supported Access Points
Cisco IOS XE Cupertino 17.7.1	17.7.1.11	15.3(3)JPL	<p>Cisco Catalyst APs: *9130 (I/E), 9124, *9124 (P), 9117, 9115, *9105 (I/W)</p> <p>*9130 (I/E): VID 02 or earlier</p> <p>*9120 (I/E): VID 06 or earlier</p> <p>*9105 (I): VID 03 or earlier</p> <p>*9105 (W): VID 01</p> <p>Cisco Aironet APs: 1815, 1830, 1840, 1850, 4800</p> <p>Cisco Catalyst Industrial Wireless 6300 H Series Access Points</p> <p><b>Note</b> 9136I only with Cisco Catalyst 9800 with Embedded Wireless Controller mode.</p>
Cisco IOS XE Bengaluru 17.6.5	17.6.5.22	15.3(3)JPK6	<p>Cisco Catalyst APs: 9130 (I/E), 9124 (I/E), 9117, 9115, 9105 (I/W)</p> <p>Cisco Aironet APs: 1815, 1830, 1840, 1850, 4800</p> <p>Cisco Catalyst Industrial Wireless 6300 H Series Access Points</p>
Cisco IOS XE Bengaluru 17.6.4	17.6.4.56	15.3(3)JPK5	<p>Cisco Catalyst APs: 9130 (I/E), 9124 (I/E), 9117, 9115, 9105 (I/W)</p> <p>Cisco Aironet APs: 1815, 1830, 1840, 1850, 4800</p> <p>Cisco Catalyst Industrial Wireless 6300 H Series Access Points</p>

IOS XE Releases	Access Point Image Version Number	Access Point Release	Supported Access Points
Cisco IOS XE Bengaluru 17.6.3	17.6.3.33	15.3(3)JPK4	Cisco Catalyst APs: *9130 (I/E), 9124, 9120 (P), 9117, 9115, *9105 (I/W) *9130 (I/E): VID 02 or earlier *9120 (I/E): VID 06 or earlier *9105 (I): VID 03 or earlier *9105 (W): VID 01 Cisco Aironet APs: 1815, 1830, 1840, 4800 Cisco Catalyst Industrial Wireless 6300 Access Points
Cisco IOS XE Bengaluru 17.6.2	17.6.2.43	15.3(3)JPK3	Cisco Catalyst APs: *9130 (I/E), 9124, 9120 (P), 9117, 9115, *9105 (I/W) *9130 (I/E): VID 02 or earlier *9120 (I/E): VID 06 or earlier *9105 (I): VID 03 or earlier *9105 (W): VID 01 Cisco Aironet APs: 1815, 1830, 1840, 4800 Cisco Catalyst Industrial Wireless 6300 Access Points
Cisco IOS XE Bengaluru 17.6.1	17.6.1.13	15.3(3)JPK2	Cisco Catalyst APs: *9130 (I/E), 9124, 9120 (P), 9117, 9115, *9105 (I/W) *9130 (I/E): VID 02 or earlier *9120 (I/E): VID 06 or earlier *9105 (I): VID 03 or earlier *9105 (W): VID 01 Cisco Aironet APs: 1815, 1830, 1840, 4800 Cisco Catalyst Industrial Wireless 6300 Access Points

IOS XE Releases	Access Point Image Version Number	Access Point Release	Supported Access Points
Cisco IOS XE Bengaluru 17.5.1	17.5.1.12	15.3(3)JPK1	<p>Cisco Catalyst APs: *9130 (I/E), *9120 (I/E), 9115, *9105 (I/W)</p> <p>*9130 (I/E): VID 02 or earlier</p> <p>*9120 (I/E): VID 06 or earlier</p> <p>*9105 (I): VID 03 or earlier</p> <p>*9105 (W): VID 01</p> <p>Cisco Aironet APs: 1800 (1815, 1830, 1840, 3800, 4800 Series Access Points</p> <p>Cisco Catalyst Industrial Wireless 6300 H Access Points</p>
Cisco IOS XE Bengaluru 17.4.1	17.4.1.6	15.3(3)JPK	<p>Cisco Catalyst APs: *9130 (I/E), *9120 (I/E), 9115, *9105 (I/W)</p> <p>*9130 (I/E): VID 02 or earlier</p> <p>*9120 (I/E): VID 06 or earlier</p> <p>*9105 (I): VID 03 or earlier</p> <p>*9105 (W): VID 01</p> <p>Cisco Aironet APs: 1800 (1815, 1830, 1840, 3800, 4800 Series Access Points</p> <p>Cisco Catalyst Industrial Wireless 6300 H Access Points</p>
Cisco IOS XE Amsterdam 17.3.7	17.3.7.36	15.3(3)JPJ10	<p>Cisco Catalyst APs: 9130 (I/E), 9120 (I/E), 9115, 9105 (I/W)</p> <p>Cisco Aironet APs: 1800I, 1810 OEAP, 1815, 1840, 1850, 2800, 3800, 4800 Series Access Points</p> <p>Cisco Catalyst Industrial Wireless 6300 H Access Points</p>
Cisco IOS XE Amsterdam 17.3.6	17.3.6.76	15.3(3)JPJ9	<p>Cisco Catalyst APs: 9130 (I/E), 9120 (I/E), 9115, 9105 (I/W)</p> <p>Cisco Aironet APs: 1800I, 1810 OEAP, 1815, 1840, 1850, 2800, 3800, 4800 Series Access Points</p> <p>Cisco Catalyst Industrial Wireless 6300 H Access Points</p>



IOS XE Releases	Access Point Image Version Number	Access Point Release	Supported Access Points
Cisco IOS XE Amsterdam 17.3.5b	17.3.5.43	15.3(3)JPJ8b	Cisco Catalyst APs: *9130 (I/E), *9120 9115, *9105 (I/W) *9130 (I/E): VID 02 or earlier *9120 (I/E): VID 06 or earlier *9105 (I): VID 03 or earlier *9105 (W): VID 01 Cisco Aironet APs: 1800I, 1810 OEAP, 1840, 1850, 2800, 3800, 4800 Series A Cisco Catalyst Industrial Wireless 6300 Access Points
Cisco IOS XE Amsterdam 17.3.5a	17.3.5.42	15.3(3)JPJ8a	Cisco Catalyst APs: *9130 (I/E), *9120 9115, *9105 (I/W) *9130 (I/E): VID 02 or earlier *9120 (I/E): VID 06 or earlier *9105 (I): VID 03 or earlier *9105 (W): VID 01 Cisco Aironet APs: 1800I, 1810 OEAP, 1840, 1850, 2800, 3800, 4800 Series A Cisco Catalyst Industrial Wireless 6300 Access Points
Cisco IOS XE Amsterdam 17.3.4c	17.3.4.40	15.3(3)JPJ7c	Cisco Catalyst APs: *9130 (I/E), *9120 9115, *9105 (I/W) *9130 (I/E): VID 02 or earlier *9120 (I/E): VID 06 or earlier *9105 (I): VID 03 or earlier *9105 (W): VID 01 Cisco Aironet APs: 1800I, 1810 OEAP, 1840, 1850, 2800, 3800, 4800 Series A Cisco Catalyst Industrial Wireless 6300 Access Points

IOS XE Releases	Access Point Image Version Number	Access Point Release	Supported Access Points
Cisco IOS XE Amsterdam 17.3.4	17.3.4.30	15.3(3)JPJ7	Cisco Catalyst APs: *9130 (I/E), *9120 (I/E), *9115, *9105 (I/W) *9130 (I/E): VID 02 or earlier *9120 (I/E): VID 06 or earlier *9105 (I): VID 03 or earlier *9105 (W): VID 01 Cisco Aironet APs: 1800I, 1810 OEAP, 1840, 1850, 2800, 3800, 4800 Series Access Points Cisco Catalyst Industrial Wireless 6300 H Series Access Points
Cisco IOS XE Amsterdam 17.3.3	17.3.3.26	15.3(3)JPJ6	Cisco Catalyst APs: *9130 (I/E), *9120 (I/E), *9115, *9105 (I/W)
Cisco IOS XE Amsterdam 17.3.2a	17.3.2.32	15.3(3)JPJ5	*9130 (I/E): VID 02 or earlier
Cisco IOS XE Amsterdam 17.3.1	17.3.1.9	15.3(3)JPJ4	*9120 (I/E): VID 06 or earlier *9105 (I): VID 03 or earlier *9105 (W): VID 01 Cisco Aironet APs: 1800I, 1810 OEAP, 1840, 1850, 2800, 3800, 4800 Series Access Points Cisco Catalyst Industrial Wireless 6300 H Series Access Points
Cisco IOS XE Amsterdam 17.2.1a	17.2.1.15	15.3(3)JPJ3a	Cisco Catalyst APs: *9130 (I/E), *9120 (I/E), *9115, *9105 (I/W)
Cisco IOS XE Amsterdam 17.2.1	17.2.1.11	15.3(3)JPJ3	*9130 (I/E): VID 02 or earlier
Cisco IOS XE Gibraltar 17.1.1t	17.1.1.32	15.3(3)JPJ2t	*9120 (I/E): VID 06 or earlier
Cisco IOS XE Gibraltar 17.1.1s	17.1.1.29	15.3(3)JPJ2	*9105 (I): VID 03 or earlier *9105 (W): VID 01 Cisco Aironet APs: 1800I, 1810 OEAP, 1840, 1850, 2800, 3800, 4800 Series Access Points Cisco Catalyst Industrial Wireless 6300 H Series Access Points

IOS XE Releases	Access Point Image Version Number	Access Point Release	Supported Access Points
Cisco IOS XE Gibraltar 16.12.8	16.12.8.5	15.3(3)JPI10	Cisco Catalyst APs: *9130 (I/E), *9120, 9115 *9130 (I/E): VID 02 or earlier *9120 (I/E): VID 06 or earlier  Cisco Aironet APs: 1800I, 1810 OEAP, 1840, 1850, 2800, 3800, 4800 Series A
Cisco IOS XE Gibraltar 16.12.7	16.12.7.2	15.3(3)JPI9	
Cisco IOS XE Gibraltar 16.12.6a	16.12.6.7	15.3(3)JPI8a	
Cisco IOS XE Gibraltar 16.12.5	16.12.5.13	15.3(3)JPI7	
Cisco IOS XE Gibraltar 16.12.4a	16.12.4.31	15.3(3)JPI6a	
Cisco IOS XE Gibraltar 16.12.3	16.12.3.13	15.3(3)JPI5	
Cisco IOS XE Gibraltar 16.12.2s	16.12.2.132	15.3(3)JPI4	Cisco Catalyst APs: *9130 (I/E), *9120, 9115 *9130 (I/E): VID 02 or earlier *9120 (I/E): VID 06 or earlier  Cisco Aironet APs: 1800I, 1810 OEAP, 1840, 1850, 2800, 3800, 4800 Series A

## Supported Access Points in Cisco AireOS Wireless Software Releases

Table 6: Cisco AireOS Controller Software Releases, AP IOS Releases, and Supported Access Points

Cisco AireOS Controller Release	Access Point IOS Release	Supported Access Points
8.10.185.0	15.3(3)JK9	Lightweight APs: 9130E, 9130I, 9120, 9117, 9115, 9105, 1810 OEAP, 1810W, 1815i, 1815m, 1815t, 1815w, 1830, 2700, 2800, 3702e, 3702i, 3702p, 3800, 4800, 700, 700V  Integrated Access Point on Cisco 1100 ISR, Cisco 1101, ASA5506W-AP702  Outdoor and Industrial APs: 1532E, 1532I, 1540, 1560, IW6300 Heavy Duty Series, and 6300 Series Embedded  Modules: AIR-RM3010L-x-K9 and AIR-RM3000M
8.10.183.0	15.3(3)JK8b	
8.10.182.0	15.3(3)JK8a	
8.10.181.0	15.3(3)JK8	

Cisco AireOS Controller Release	Access Point IOS Release	Supported Access Points
8.10.171.0	15.3(3)JK7	Lightweight APs: 9130E*, 9130I*, 9120*, 9117, 9115, 9105, 1800i, 1810 OEAP, 1810W, 1815i, 1815m, 1815t, 1815w, 1850, 2700, 2800, 3702e, 3702i, 3702p, 3800, 4800, 700, 700W, AP803 *9105 <ul style="list-style-type: none"> <li>• 9105AXI: VID 04 and earlier</li> <li>• 9105AXW: VID 01</li> </ul> *9130 <ul style="list-style-type: none"> <li>• 9130AXI, 9130AXE: VID 02 and earlier</li> </ul> *9120 <ul style="list-style-type: none"> <li>• 9120AXI and 9120AXE: VID 06 and earlier</li> <li>• 9120AXP: all VIDs</li> </ul> Integrated Access Point on Cisco 1100 ISR, Cisco 1101 ISR, ASA5506W-AP702 Outdoor and Industrial APs: 1532E, 1532I, 1540, 1560, 1570, IW6300 Heavy Duty Series, and 6300 Series Embedded Series Modules: AIR-RM3010L-x-K9 and AIR-RM3000M
8.10.162.0	15.3(3)JK6	
8.10.151.0	15.3(3)JK5	
8.10.142.0	15.3(3)JK4	
8.10.130.0	15.3(3)JK3	
8.10.122.0	15.3(3)JK2a	Lightweight APs: 9130E*, 9130I*, 9120*, 9117, 9115, 1700, 1800i, 1810 OEAP, 1810W, 1815i, 1815m, 1815t, 1815w, 1830, 1840, 1850, 2700, 2800, 3702e, 3702i, 3702p, 3800, 4800, 700, 700W, AP803 *9130 <ul style="list-style-type: none"> <li>• 9130AXI, 9130AXE: VID 02 and earlier</li> </ul> *9120 <ul style="list-style-type: none"> <li>• 9120AXI and 9120AXE: VID 06 and earlier</li> <li>• 9120AXP: all VIDs</li> </ul> Integrated Access Point on Cisco 1100 ISR, Cisco 1101 ISR, ASA5506W-AP702 Outdoor and Industrial APs: 1532E, 1532I, 1540, 1560, 1570, IW6300 Heavy Duty Series, and 6300 Series Embedded Series Modules: AIR-RM3010L-x-K9 and AIR-RM3000M
8.10.121.0	15.3(3)JK2	
8.10.113.0	15.3(3)JK1t	
8.10.112.0	15.3(3)JK1	

Cisco AireOS Controller Release	Access Point IOS Release	Supported Access Points
8.10.105.0	15.3(3)JK	<p>Lightweight APs: 9130I*, 9120*, 9117, 9115, 1700, 1800, 1810W, 1815i, 1815m, 1815t, 1815w, 1830, 1840, 1850, 3702e, 3702i, 3702p, 3800, 4800, 700, 700W, AP803</p> <p>*9130</p> <ul style="list-style-type: none"> <li>• 9130AXI: VID 02 and earlier</li> </ul> <p>*9120</p> <ul style="list-style-type: none"> <li>• 9120AXI: VID 06 and earlier</li> <li>• 9120AXP: all VIDs</li> </ul> <p>Integrated Access Point on Cisco 1100 ISR, Cisco 1101 ASA5506W-AP702</p> <p>Outdoor and Industrial APs: 1532E, 1532I, 1540, 1560, IW6300 Heavy Duty Series, and 6300 Series Embedded</p> <p>Modules: AIR-RM3010L-x-K9 and AIR-RM3000M</p>
8.9.111.0	15.3(3)JJ1	<p>Lightweight APs: 9120*, 9117, 9115, 1700, 1800i, 1810, 1815i, 1815m, 1815t, 1815w, 1830, 1850, 2700, 2800, 3702p, 3800, 4800, 700, 700W, AP803</p> <p>*9120</p> <ul style="list-style-type: none"> <li>• 9120AXI: VID 06 and earlier</li> </ul> <p>Integrated Access Point on Cisco 1100 ISR, Cisco 1101 ASA5506W-AP702</p> <p>Outdoor and Industrial APs: 1532E, 1532I, 1540, 1560, IW3700</p> <p>Modules: AIR-RM3010L-x-K9 and AIR-RM3000M</p>
8.9.100.0	15.3(3)JJ	<p>Lightweight APs: 9115, 9117, 1700, 1800i, 1810 OEAP, 1815m, 1815t, 1815w, 1830, 1850, 2700, 2800, 3702e, 3800, 4800, 700, 700W, AP803</p> <p>Integrated Access Point on Cisco 1100 ISR, Cisco 1101 ASA5506W-AP702</p> <p>Outdoor and Industrial APs: 1532E, 1532I, 1540, 1560, IW3700</p> <p>Modules: AIR-RM3010L-x-K9 and AIR-RM3000M</p>

Cisco AireOS Controller Release	Access Point IOS Release	Supported Access Points
8.8.130.0	15.3(3)JI6	Lightweight APs: 1700, 1800i, 1810 OEAP, 1810W, 1815i, 1815t, 1815w, 1830, 1850, 2700, 2800, 3702e, 3702i, 3702p, 3700, 700W, AP803  Integrated Access Point on Cisco 1100 ISR, Cisco 1101 ISR, ASA5506W-AP702  Outdoor and Industrial APs: 1532E, 1532I, 1540, 1560, 1570, IW3700  Modules: AIR-RM3010L-x-K9 and AIR-RM3000M
8.8.125.0	15.3(3)JI5	
8.8.120.0	15.3(3)JI4	
8.8.111.0	15.3(3)JI3	Lightweight APs: 1700, 1800i, 1810 OEAP, 1810W, 1815i, 1815t, 1815w, 1830, 1850, 2700, 2800, 3702e, 3702i, 3702p, 3700, 700W, AP803  Integrated Access Point on Cisco 1100 ISR, Cisco 1101 ISR, ASA5506W-AP702  Outdoor and Industrial APs: 1532E, 1532I, 1540, 1560, 1570, IW3700  Modules: AIR-RM3010L-x-K9 and AIR-RM3000M
8.8.100.0	15.3(3)JI1	
8.7.106.0	15.3(3)JH1	Lightweight APs: 1700, 1800i, 1810 OEAP, 1810W, 1815i, 1815t, 1815w, 1830, 1850, 2700, 2800, 3702e, 3702i, 3702p, 3700, 700W, AP803  Integrated Access Point on Cisco 1100 ISR, ASA5506W-AP702  Outdoor and Industrial APs: 1532E, 1532I, 1540, 1560, 1570, IW3700  Modules: AIR-RM3010L-x-K9 and AIR-RM3000M
8.7.102.0	15.3(3)JH	Lightweight APs: 1700, 1800i, 1810 OEAP, 1810W, 1815i, 1815t, 1815w, 1830, 1850, 2700, 2800, 3702e, 3702i, 3702p, 3700, 700W, AP803  Integrated Access Point on Cisco 1100 ISR, ASA5506W-AP702  Outdoor and Industrial APs: 1532E, 1532I, 1540, 1560, 1570, IW3700  Modules: AIR-RM3010L-x-K9 and AIR-RM3000M

Cisco AireOS Controller Release	Access Point IOS Release	Supported Access Points
8.6.101.0	15.3(3)JG1	Lightweight APs: 1700, 1800i, 1810 OEAP, 1810W, 1815t, 1815w, 1830, 1850, 2700, 2800, 3702e, 3702i, 3700W, AP803  Integrated Access Point on Cisco 1100 ISR, ASA5506W  Outdoor and Industrial APs: 1532E, 1532I, 1540, 1560, IW3700  Modules: AIR-RM3010L-x-K9 and AIR-RM3000M
8.5.182.0	15.3(3)JF15	Lightweight APs: 1600, 1700, 1800i, 1810 OEAP, 1810W, 1815t, 1815w, 1830, 1850, 2600, 2700, 2800, 3500e, 3500i, 3600e, 3600i, 3600p, 3702e, 3702i, 3702p, 3800, 700, 700W, AP803  Integrated Access Point on Cisco 1100 ISR, ASA5506W  Outdoor and Industrial APs: 1532E, 1532I, 1540, 1552E, 1552C, 1552EU, 1552CU, 1552S, 1560, 1570, and IW3700  <b>Note</b> The Cisco Aironet 1550 Series APs with 64K are not supported.  Modules: AIR-RM3010L-x-K9 and AIR-RM3000M
8.5.171.0	15.3(3)JF14	
8.5.164.0	15.3(3)JF12i	
8.5.161.0	15.3(3)JF12	
8.5.160.0	15.3(3)JF11	
8.5.151.0	15.3(3)JF10	
8.5.140.0	15.3(3)JF9	
8.5.135.0	15.3(3)JF8	
8.5.131.0	15.3(3)JF7	
8.5.120.0	15.3(3)JF5	
8.5.110.0	15.3(3)JF4	
8.5.105.0	15.3(3)JF1	
8.5.103.0	15.3(3)JF	
8.4.100.0	15.3(3)JE	Lightweight APs: 1600, 1700, 1810 OEAP, 1810W, 1815t, 1815w, 1830, 1850, 2600, 2700, 2800, 3500e, 3500i, 3500p, 3600e, 3600i, 3600p, 3702e, 3702i, 3702p, 3800, 700, 700W, AP802, AP803, ASA5506W-AP702  Outdoor and Industrial APs: 1532E, 1532I, 1552E, 1552H, 1552EU, 1552CU, 1552S, 1560, 1570, and IW3700  <b>Note</b> The Cisco Aironet 1550 Series APs with 64K are not supported.  Modules: AIR-RM3010L-x-K9 and AIR-RM3000M

Cisco AireOS Controller Release	Access Point IOS Release	Supported Access Points
8.3.150.0	15.3(3)JD17 15.3(3)JDA17	<p>Lightweight APs: 1040, 1140, 1260, 1600, 1700, 1810 OEA, 1815i, 1830, 1850, 2600, 2700, 2800, 3500e, 3500i, 3500p, 3600p, 3702e, 3702i, 3702p, 3800, 600 OEAP, 700, 700W, AP803, ASA5506W-AP702</p> <p>Outdoor and Industrial APs: 1532E, 1532I, 1552E, 1552H, 1552EU, 1552CU, 1552S, 1560, 1570, and IW3700</p> <p>Modules: AIR-RM3010L-x-K9 and AIR-RM3000M</p> <p>The Cisco 1040 Series, 1140 Series, and 1260 Series access points feature parity with Cisco Wireless Release 8.0. Features introduced in Cisco Wireless Release 8.1 or later are not supported on these access points.</p>
8.3.143.0	15.3(3)JD16 15.3(3)JDA16	
8.3.141.0	15.3(3)JD14 15.3(3)JDA14	
8.3.140.0	15.3(3)JD13 15.3(3)JDA13	
8.3.133.0	15.3(3)JD11 15.3(3)JDA11	
8.3.132.0	15.3(3)JD9 15.3(3)JDA9	
8.3.130.0	15.3(3)JD7 15.3(3)JDA7	
8.3.122.0	15.3(3)JD6	
8.3.121.0	15.3(3)JD5	
8.3.112.0	15.3(3)JD4	



Cisco AireOS Controller Release	Access Point IOS Release	Supported Access Points
8.3.102.0	15.3(3)JD	<p>Lightweight APs: 1040, 1140, 1260, 1600, 1700, 1810 C, 1830, 1850, 2600, 2700, 2800, 3500e, 3500i, 3500p, 3600e, 3702e, 3702i, 3702p, 3800, 600 OEAP, 700, 700W, AP8, ASA5506W-AP702</p> <p>Outdoor and Industrial APs: 1532E, 1532I, 1552E, 1552H, 1552EU, 1552CU, 1552S, 1570, and IW3700</p> <p>Modules: AIR-RM3010L-x-K9 and AIR-RM3000M</p> <p><b>Note</b> The Cisco 1040 Series, 1140 Series, and 1260 Series access points have feature parity with Cisco Wireless Software Releases. Features introduced in Cisco Wireless Software Releases are not supported on these access points.</p>
8.2.170.0	15.3(3)JC15	<p>Lightweight APs: 1040, 1140, 1260, 1600, 1700, 1810 C, 1830, 1850, 2600, 2700, 2800, 3500e, 3500i, 3500p, 3600e, 3702e, 3702i, 3702p, 3800, 600 OEAP, 700, 700W, AP8, ASA5506W-AP702</p> <p>Outdoor and Industrial APs: 1532E, 1532I, 1552E, 1552H, 1552EU, 1552CU, 1552S, 1570, and IW3700</p> <p>Modules: AIR-RM3010L-x-K9 and AIR-RM3000M</p> <p><b>Note</b> The Cisco 1040 Series, 1140 Series, and 1260 Series access points have feature parity with Cisco Wireless Software Releases. Features introduced in Cisco Wireless Software Releases are not supported on these access points.</p>
8.2.166.0	15.3(3)JC14	
	15.3(3)JCA14	
8.2.164.0	15.3(3)JC9	<p>Lightweight APs: 1040, 1140, 1260, 1600, 1700, 1810 C, 1830, 1850, 2600, 2700, 2800, 3500e, 3500i, 3500p, 3600e, 3702e, 3702i, 3702p, 3800, 600 OEAP, 700, 700W, AP8, ASA5506W-AP702</p> <p>Outdoor and Industrial APs: 1532E, 1532I, 1552E, 1552H, 1552EU, 1552CU, 1552S, 1570, and IW3700</p> <p>Modules: AIR-RM3010L-x-K9 and AIR-RM3000M</p> <p><b>Note</b> The Cisco 1040 Series, 1140 Series, and 1260 Series access points have feature parity with Cisco Wireless Software Releases. Features introduced in Cisco Wireless Software Releases are not supported on these access points.</p>
	15.3(3)JCA9	
8.2.161.0	15.3(3)JC8	<p>Lightweight APs: 1040, 1140, 1260, 1600, 1700, 1810 C, 1830, 1850, 2600, 2700, 2800, 3500e, 3500i, 3500p, 3600e, 3702e, 3702i, 3702p, 3800, 600 OEAP, 700, 700W, AP8, ASA5506W-AP702</p> <p>Outdoor and Industrial APs: 1532E, 1532I, 1552E, 1552H, 1552EU, 1552CU, 1552S, 1570, and IW3700</p> <p>Modules: AIR-RM3010L-x-K9 and AIR-RM3000M</p> <p><b>Note</b> The Cisco 1040 Series, 1140 Series, and 1260 Series access points have feature parity with Cisco Wireless Software Releases. Features introduced in Cisco Wireless Software Releases are not supported on these access points.</p>
	15.3(3)JCA8	
8.2.160.0	15.3(3)JC7	
8.2.151.0	15.3(3)JC6	<p>Lightweight APs: 1040, 1140, 1260, 1600, 1700, 1810 C, 1830, 1850, 2600, 2700, 2800, 3500e, 3500i, 3500p, 3600e, 3702e, 3702i, 3702p, 3800, 600 OEAP, 700, 700W, AP8, ASA5506W-AP702</p> <p>Outdoor and Industrial APs: 1532E, 1532I, 1552E, 1552H, 1552EU, 1552CU, 1552S, 1570, and IW3700</p> <p>Modules: AIR-RM3010L-x-K9 and AIR-RM3000M</p> <p><b>Note</b> The Cisco 1040 Series, 1140 Series, and 1260 Series access points have feature parity with Cisco Wireless Software Releases. Features introduced in Cisco Wireless Software Releases are not supported on these access points.</p>
8.2.141.0	15.3(3)JC5	
8.2.130.0	15.3(3)JC4	
8.2.121.0	15.3(3)JC3	

Cisco AireOS Controller Release	Access Point IOS Release	Supported Access Points
8.2.111.0	15.3(3)JC2	<p>Lightweight APs: 1040, 1140, 1260, 1600, 1700, 1810 OEA, 1830, 1850, 2600, 2700, 2800, 3500e, 3500i, 3500p, 3600e, 3600i, 3702e, 3702i, 3702p, 3800, 600 OEAP, 700, 700W, AP802, ASA5506W-AP702</p> <p>Outdoor and Industrial APs: 1532E, 1532I, 1552E, 1552H, 1552EU, 1552CU, 1552S, 1570, and IW3700</p> <p>Modules: AIR-RM3010L-x-K9 and AIR-RM3000M</p> <p><b>Note</b> The Cisco 1040 Series, 1140 Series, and 1260 Series access points have feature parity with Cisco Wireless Release 8.2.111.0. Features introduced in Cisco Wireless Release 8.2.111.0 are not supported on these access points.</p>
8.2.110.0	15.3(3)JC1	<p>Lightweight APs: 1040, 1140, 1260, 1600, 1700, 1810 OEA, 1830, 1850, 2600, 2700, 2800, 3500e, 3500i, 3500p, 3600e, 3600i, 3702e, 3702i, 3702p, 3800, 600 OEAP, 700, 700W, AP802, ASA5506W-AP702</p> <p>Outdoor and Industrial APs: 1532E, 1532I, 1552E, 1552H, 1552EU, 1552CU, 1552S, 1570, and IW3700</p> <p>Modules: AIR-RM3010L-x-K9 and AIR-RM3000M</p> <p><b>Note</b> The Cisco 1040 Series, 1140 Series, and 1260 Series access points have feature parity with Cisco Wireless Release 8.2.110.0. Features introduced in Cisco Wireless Release 8.2.110.0 are not supported on these access points.</p> <p><b>Note</b> Initial support for –B regulatory domain APs.</p>
8.2.100.0	15.3(3)JC	<p>Lightweight APs: 1040, 1140, 1260, 1600, 1700, 1830, 1850, 2700, 3500e, 3500i, 3500p, 3600e, 3600i, 3600p, 3702e, 3702i, 3702p, 600 OEAP, 700, 700W, AP802, AP803, ASA5506W-AP702</p> <p>Outdoor and Industrial APs: 1532E, 1532I, 1552E, 1552H, 1552EU, 1552CU, 1552S, 1570, and IW3700</p> <p>Modules: AIR-RM3010L-x-K9 and AIR-RM3000M</p> <p><b>Note</b> The Cisco 1040 Series, 1140 Series, and 1260 Series access points have feature parity with Cisco Wireless Release 8.2.100.0. Features introduced in Cisco Wireless Release 8.2.100.0 are not supported on these access points.</p>

Cisco AireOS Controller Release	Access Point IOS Release	Supported Access Points
8.1.131.0	15.3(3)JBB6	<p>Lightweight APs: 1040, 1140, 1260, 1600, 1700, 1830, 2700, 3500e, 3500i, 3500p, 3600e, 3600i, 3600p, 3702e, 600 OEAP, 700, 700W, AP802, AP803, ASA5506W-AF</p> <p>Outdoor and Industrial APs: 1532E, 1532I, 1552E, 1552H, 1552EU, 1552CU, 1552S, 1570, and IW3700</p> <p>Modules: AIR-RM3010L-x-K9 and AIR-RM3000M</p> <p><b>Note</b> The Cisco 1040 Series, 1140 Series, and 1260 Series access points have feature parity with Cisco Wireless Software Releases. Features introduced in Cisco Wireless Software Releases are not supported on these access points.</p>
8.1.122.0	15.3(3)JBB5	<p>Lightweight APs: 1040, 1140, 1260, 1600, 1700, 1830, 2700, 3500e, 3500i, 3500p, 3600e, 3600i, 3600p, 3702e, 600 OEAP, 700, 700W, AP802, AP803, ASA5506W-AF</p> <p>Outdoor and Industrial APs: 1532E, 1532I, 1552E, 1552H, 1552EU, 1552CU, 1552S, 1570, and IW3700</p> <p><b>Note</b> The Cisco 1040 Series, 1140 Series, and 1260 Series access points have feature parity with Cisco Wireless Software Releases. Features introduced in Cisco Wireless Software Releases are not supported on these access points.</p>
8.1.111.0	15.3(3)JBB1	<p>Lightweight APs: 1040, 1140, 1260, 1600, 1700, 1850, 2700, 3500e, 3500i, 3500p, 3600e, 3600i, 3600p, 3702e, 3702i, 600 OEAP, 700, 700W, and AP802</p> <p>Outdoor and Industrial APs: 1532E, 1532I, 1552E, 1552H, 1552EU, 1552CU, 1552S, and 1570</p> <p><b>Note</b> The Cisco 1040 Series, 1140 Series, and 1260 Series access points have feature parity with Cisco Wireless Software Releases. Features introduced in Cisco Wireless Software Releases are not supported on these access points.</p>
8.1.102.0	15.3(3)JBB	<p>Lightweight APs: 1040, 1140, 1260, 1600, 1700, 2600, 2700, 3500i, 3500p, 3600e, 3600i, 3600p, 3702e, 3702i, 3702p, 700, 700W, and AP802</p> <p>Outdoor and Industrial APs: 1532E, 1532I, 1552E, 1552H, 1552EU, 1552CU, 1552S, and 1570</p> <p><b>Note</b> The Cisco 1040 Series, 1140 Series, and 1260 Series access points have feature parity with Cisco Wireless Software Releases. Features introduced in Cisco Wireless Software Releases are not supported on these access points.</p>



Cisco AireOS Controller Release	Access Point IOS Release	Supported Access Points
8.0.100.0	15.3(3)JAB 12.4(25e)JAP	Lightweight APs: 1040, 1130, 1140, 1240, 1250, 1260, 1260p, 2600, 2700, 3500e, 3500i, 3500p, 3600e, 3600i, 3600p, 3702p, 600 OEAP, 700, 700W, AP801, and AP802  Outdoor and Industrial APs: 1522, 1524PS, 1524SB, 1524SE, 1552E, 1552H, 1552I, 1552C, 1552EU, 1552CU, and 1552EU

## Related Information

- See the relevant release notes before you perform any software upgrade:  
<https://www.cisco.com/c/en/us/support/wireless/wireless-lan-controller-software/products-release-notes-list.html>
- Product Approval Status: <https://cae-cnc-prd.cisco.com/pdtncc/#/>
- Wireless LAN Compliance Lookup:  
<https://www.cisco.com/c/dam/assets/prod/wireless/wireless-compliance-tool/index.html>

## Access Point Specific Wireless Controller Software Support

This section lists the Cisco Wireless Controller software releases that support specific Cisco Access Points. The First Support column lists the earliest Cisco Controller software release that supports the access point module. For access points not supported in ongoing releases, the Last Support column lists the last release that supported the access points.

**Table 7: Software Support for Access Point Modules**

Access Points	PID	First AireOS Release Support	Last AireOS Release Support	First Cisco IOS XE Release Support	Last Cisco IOS XE Release Support
1810 Series	AIR-OEAP1810-x-K9	8.2.110.0	8.10.x	Cisco IOS XE Gibraltar 16.10.1	Cisco IOS XE Amsterdam 17.3.x
1810W Series	AIR-AP1810W-x-K9	8.2.110.0	8.10.x	Cisco IOS XE Gibraltar 16.10.1	Cisco IOS XE Amsterdam 17.3.x
1815 Series	AIR-AP1815I-x-K9	8.3.112.0	8.10.x	Cisco IOS XE Gibraltar 16.10.1	—
	AIR-AP1815W-x-K9	8.4.100.0	8.10.x		—
	AIR-AP1815M-x-K9	8.5.103.0	8.10.x		—
	AIR-AP1815T-x-K9	8.5.103.0	8.10.x		—

Access Points	PID	First AireOS Release Support	Last AireOS Release Support	First Cisco IOS XE Release Support	Last Cisco IOS XE Release Support				
1830 Series	AIR-AP1832I-U XK9	8.1.122.0	8.10.x	Cisco IOS XE Gibraltar 16.10.1	—				
	AIR-AP1832I-U XK910				—				
	AIR-AP1832I-U XK9C				—				
	AIR-AP1832I-U XK910C				—				
	AIR-AP1832I-x-K9				—				
	AIR-AP1832I-x-K9C				—				
1840 Series	AIR-AP1840I-x-K9C	8.10.105.0	8.10.x	Cisco IOS XE Gibraltar 16.12.1	—				
1850 Series	AIR-AP1852I-U XK9	8.1.111.0	8.10.x	Cisco IOS XE Gibraltar 16.10.1	—				
	AIR-AP1852I-U XK910				—				
	AIR-AP1852I-U XK9C				—				
	AIR-AP1852I-U XK910C				—				
	AIR-AP1852E-U XK9				—				
	AIR-AP1852E-U XK910				—				
	AIR-AP1852E-U XK9C	8.1.111.0	8.10.x	Cisco IOS XE Gibraltar 16.10.1	—				
	AIR-AP1852E-U XK910C				—				
	AIR-AP1852E-x-K9				—				
	AIR-AP1852E-x-K9C				—				
	AIR-AP1852I-x-K9				—				
	AIR-AP1852I-x-K9C				—				
	Integrated Access Point on Cisco 1100 ISR				ISR-AP1100AC-X	8.5.103.0	8.10.x	— Cisco IOS XE Gibraltar 16.10.1e	—
	Integrated Access Point on Cisco 1101 ISR				ISR-AP1101AC-X	8.8.100.0	8.10.x	—	—
ISR-AP1101AC-I-X		—	—						

Access Points	PID	First AireOS Release Support	Last AireOS Release Support	First Cisco IOS XE Release Support	Last Cisco IOS XE Release Support
1700 Series	AIR-CAP1702I	7.6.100.0	8.10.x	Cisco IOS XE Denali 16.3.1	Cisco IOS XE Amsterdam 17.3.x Cisco IOS XE Cupertino 17.9.3 <b>Note</b> This AP is not supported in releases 17.4.1 – 17.9.2.
2700 Series	AIR-CAP2702I	7.6.100.0	8.10.x	Cisco IOS XE Denali 16.3.1	Cisco IOS XE Amsterdam 17.3.x Cisco IOS XE Cupertino 17.9.3 <b>Note</b> This AP is not supported in releases 17.4.1 – 17.9.2.
	AIR-CAP2702E				
2800 Series	AIR-AP2802E-x-K9	8.2.110.0	8.10.x	Cisco IOS XE Denali 16.3.1	—
	AIR-AP2802I-x-K9				—
3700 Series	AIR-CAP3702I	7.6.100.0	8.10.x	3.3.1SE	Cisco IOS XE Amsterdam 17.3.x Cisco IOS XE Cupertino 17.9.3 <b>Note</b> This AP is not supported in releases 17.4.1 – 17.9.2.
	AIR-CAP3702E				
	AIR-CAP3702P				

Access Points	PID	First AireOS Release Support	Last AireOS Release Support	First Cisco IOS XE Release Support	Last Cisco IOS XE Release Support
3800 Series	AIR-AP3802E-x-K9	8.2.110.0	8.10.x	Cisco IOS XE Denali 16.3.1	—
	AIR-AP3802I-x-K9				—
	AIR-AP3802P-x-K9				—
4800 Series	AIR-AP4800-x-K9	8.7.106.0	8.10.x	Cisco IOS XE Gibraltar 16.10.1	—
	AIR-AP4800-x-K9C				—
9136	C9136I-x	—	—	Cisco IOS XE Cupertino 17.7.1	—
916X Series	CW9162I-x	—	—	Cisco IOS XE Cupertino 17.9.2	—
	CW9164I-x	—	—	Cisco IOS XE Cupertino 17.9.1	—
	CW9166I-x	—	—		
9130	C9130AXE-STA-x	—	—	Cisco IOS XE Amsterdam 17.3.6 Cisco IOS XE Bengaluru 17.6.4	—
	C9130AXE-x	8.10.181.0	8.10.x	Cisco IOS XE Amsterdam 17.3.6 Cisco IOS XE Bengaluru 17.6.4	—
	C9130AXI-x	8.10.181.0	8.10.x	Cisco IOS XE Amsterdam 17.3.6 Cisco IOS XE Bengaluru 17.6.4	—
	C9130AXE-STA-x VID 02 or earlier	—	—	Cisco IOS XE Bengaluru 17.6.1	—
	C9130AXE-x VID 02 or earlier	8.10.112.0	8.10.x	Cisco IOS XE Amsterdam 17.3.1	—
	C9130AXI-x VID 02 or earlier	8.10.105.0	8.10.x	Cisco IOS XE Gibraltar 16.12.2s	—



Access Points	PID	First AireOS Release Support	Last AireOS Release Support	First Cisco IOS XE Release Support	Last Cisco IOS XE Release Support
9124	C9124AXI-x	—	—	Cisco IOS XE Bengaluru 17.5.1	—
	C9124AXD-x	—	—	Cisco IOS XE Amsterdam 17.3.4c (A, B, E, Q, Z, F, and R Domains) Cisco IOS XE Amsterdam 17.3.4 (B Domain) Cisco IOS XE Bengaluru 17.6.2 (For all Regulatory Domains)	—
	C9124AXE-x	—	—	Bengaluru 17.6.2 Cisco IOS XE Amsterdam 17.3.5a (A, B, E, and Z Domains)	—
9120 <sup>1</sup>	C9120AXE-x	8.10.181.0	8.10.x	Cisco IOS XE Amsterdam 17.3.6 Cisco IOS XE Bengaluru 17.6.4	—
	C9120AXI-x	8.10.181.0	8.10.x	Cisco IOS XE Amsterdam 17.3.6 Cisco IOS XE Bengaluru 17.6.4	—
	C9120AXE-x VID 06 or earlier	8.10.112.0	8.10.x	Cisco IOS XE Gibraltar 16.12.2s	—
	C9120AXI-x VID 06 or earlier	8.9.111.0	8.10.x	Cisco IOS XE Gibraltar 16.11.1b	—
	C9120AXP-x All VIDs	8.9.111.0	8.10.x	Cisco IOS XE Gibraltar 16.12.2s	—
9117	C9117AXI-x	8.9.100.0	8.10.x	Cisco IOS XE Gibraltar 16.11.1b	—

Access Points	PID	First AireOS Release Support	Last AireOS Release Support	First Cisco IOS XE Release Support	Last Cisco IOS XE Release Support
9115	C9115AXI-x	8.9.100.0	8.10.x	Cisco IOS XE Gibraltar 16.11.1b	—
	C9115AXE-x		8.10.x		—
9105	C9105AX-W	8.10.181.0	8.10.x	Cisco IOS XE Amsterdam 17.3.6 Cisco IOS XE Bengaluru 17.6.4	—
	C9105AX-I	8.10.181.0	8.10.x	Cisco IOS XE Amsterdam 17.3.6 Cisco IOS XE Bengaluru 17.6.4	—
	C9105AX-W VID 03 or earlier	8.10.130.0	8.10.x	Cisco IOS XE Amsterdam 17.3.1	—
	C9105AX-I VID 03 or earlier	8.10.130.0	8.10.x	Cisco IOS XE Amsterdam 17.3.1	—
1530 Series	AIR-CAP1532I-x-K9	7.6.100.0	8.10.x	3.6.0E <sup>3</sup>	Cisco IOS XE 16.3.x
	AIR-CAP1532E-x-K9				
1540 Series	AIR-AP1542I-x-K9	8.5.103.0	8.10.x	Cisco IOS XE Gibraltar 16.10.1	—
	AIR-AP1542D-x-K9				—
1550 Series <sup>4</sup>	AIR-CAP1552I-x-K9	7.0.116.0	8.5.x	—	—
	AIR-CAP1552E-x-K9	7.0.116.0		—	—
	AIR-CAP1552C-x-K9	7.0.116.0		—	—
	AIR-CAP1552H-x-K9	7.0.116.0		—	—
	AIR-CAP1552SA-x-K9	7.0.220.0		—	—
	AIR-CAP1552SD-x-K9	7.0.220.0		—	—
	AIR-CAP1552CU-x-K9	7.3.101.0		—	—
	AIR-CAP1552EU-x-K9	7.3.101.0		—	—
1552S	AIR-CAP1552SA-x-K9	7.0.220.0	8.5.x	—	—
	AIR-CAP1552SD-x-K9				—

Access Points	PID	First AireOS Release Support	Last AireOS Release Support	First Cisco IOS XE Release Support	Last Cisco IOS XE Release Support	
1560 Series	AIR-AP1562I-x-K9	8.3.111.0	8.10.x	Cisco IOS XE Gibraltar 16.10.1	—	
	AIR-AP1562E-x-K9				—	
	AIR-AP1562D-x-K9				—	
1570 version ID 01 (V01)	AIR-AP1572EAC-x-K9	8.0.110.0	8.10.x	Cisco IOS XE Gibraltar 16.10.1	Cisco IOS XE Amsterdam 17.3.x	
	AIR-AP1572ICy-x-K9 <sup>5</sup>				Cisco IOS XE Cupertino 17.9.3	
	AIR-AP1572ECy-x-K9				<b>Note</b> This AP is not supported in releases 17.4.1 – 17.9.2.	
1570 version ID 02 (V02)	AIR-AP1572EAC-B-K9	8.0.135.0	8.10.x	—	—	
	AIR-AP1572EC1-B-K9			—	—	
	AIR-AP1572EC2-B-K9			Cisco IOS XE Gibraltar 16.10.x	Cisco IOS XE Amsterdam 17.3.x	
	AIR-AP1572IC1-B-K9					Cisco IOS XE Cupertino 17.9.3
	AIR-AP1572IC2-B-K9					

Access Points	PID	First AireOS Release Support	Last AireOS Release Support	First Cisco IOS XE Release Support	Last Cisco IOS XE Release Support
IW3700	IW3702-2E-U XK9	8.0.120.0	8.10.x	—	—
	IW3702-4E-U XK9	8.0.120.0		—	—
	IW3702-2E-B-K9	8.2.110.0		—	—
	IW3702-4E-B-K9	8.2.110.0		—	—
	IW3702-2E-M-K9	8.3.102.0		—	—
	IW3702-4E-M-K9	8.3.102.0		Cisco IOS XE Gibraltar 16.11.1c	—
	IW3702-2E-R-K9	8.3.102.0			—
	IW3702-4E-R-K9	8.3.102.0			—
	IW3702-2E-Q-K9	8.3.102.0			—
	IW3702-4E-Q-K9	8.3.102.0			—
	IW3702-2E-S-K9	8.3.102.0			—
	IW3702-4E-S-K9	8.3.102.0		—	
IW6300 Heavy Duty	IW-6300H-AC-x-K9	8.10.105.0	8.10.x	Cisco IOS XE Gibraltar 17.1.1s	—
	IW-6300H-DCW-x-K9				—
	IW-6300H-DC-x-K9				—
6300 Embedded Services	ESW-6300-CON-x-K9	8.10.105.0	8.10.x	Cisco IOS XE Gibraltar 17.1.1s	—

1	Cisco Catalyst 9130, 9120, 9117, 9115 Access Points Regulatory domains: Customers are responsible for verifying approval for use in their individual countries. To verify approval and to identify the regulatory domain that corresponds to a particular country, visit <a href="https://www.cisco.com/go/aironet/compliance">https://www.cisco.com/go/aironet/compliance</a> . Not all regulatory domains have been approved. As they are approved, the part numbers will be available on the Global Price List.
2	These access points are supported in the separate 4.1.19x.x mesh software release or with release 5.2 or later releases. These access points are not supported in the 4.2, 5.0, or 5.1 Releases.
3	The Cisco Aironet 1530 Series APs are supported operating only in Local mode; these APs in mesh mode are not supported.
4	The Cisco Aironet 1550 Series APs with 64-MB memory are not supported from Release 8.4.
5	y—Country DOCSIS Compliance, see ordering guide for details.

## Cisco AireOS Wireless Controller Specific Software Release Support

This section lists the Cisco AireOS Wireless controller software releases in which the support started and ended, as applicable, for various Cisco AireOS Wireless Controller hardware platforms.

**Table 8: Cisco AireOS Wireless Controller Platform Support in Software Releases**

Cisco Wireless Controller Platform	First Support	Last Support
2100	4.2.x	7.x
2504	7.0.x	8.5
3504	8.5	8.10.x
4400	4.2.x	7.x
5508	6.0.x	8.5
5520	8.1.x	8.10.x
7510	7.0.x	8.5
8510	7.3.x	8.5
8540	8.1.x	8.10.x
Virtual Controller	7.3.x	8.10.x
WiSM	4.2.x	7.x
WiSM2 (1 DP)	7.0.x	8.5
WiSM2 (2 DP)	7.2.x	8.5
SRE	7.0.x	8.10.x

For information about supported hardware for Cisco Converged Access Solution, see [Supported Converged Access Solutions](#) section in the *Compatibility Matrix for Legacy Cisco Wireless Solutions* document.

## Cisco Aironet 1800s Active Sensor Compatibility Matrix

[Table 9: Cisco Aironet 1800s Active Sensor Compatibility Matrix, on page 69](#) lists various Cisco Aironet 1800s Active Sensor software releases and the corresponding supported Cisco DNA Center versions.

**Table 9: Cisco Aironet 1800s Active Sensor Compatibility Matrix**

Cisco Aironet 1800s Active Sensor Software	Cisco DNA Center
2.2.2.0	2.2.2.x

Cisco Aironet 1800s Active Sensor Software	Cisco DNA Center
2.2.1.0	2.2.1.x
2.1.1.0	2.1.1.x
1.3.3.0	1.3.3.x
1.3.1.2	1.3.1.2
8.8.263.0	1.3.0.3 or earlier
8.8.261.0	
8.8.259.0	
8.8.258.0	
8.7.258.0	

## Inter Release Compatibility Matrix within Platforms

### Inter Release Compatibility Matrix between IOS-XE Software Platforms

Table 10: IRCM for IOS-XE Releases

Base Release Number	Compatible Release Number
17.3.5a	17.9.1
17.3.4c	17.9.1
17.3.4	17.9.1

### Inter Release Compatibility Matrix between AireOS Releases

Mobility, or roaming, is a wireless LAN client's ability to maintain its association seamlessly from one AP to another securely and with as little latency as possible. For more information about mobility in AireOS releases, see the *Information About Mobility* section in the [Controller configuration guide](#).

This section lists compatibility information between various AireOS releases, starting from 8.0.x, that involve Layer 2 and Layer 3 roaming and guest tunneling.

Table 11: IRCM Compatibility Matrix: 8.0.x to Later Releases

Release	8.0x	8.2x	8.3x	8.4x	8.5x	8.6x	8.7x	8.8x	8.9x	8.10x
8.0.x	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y
8.2.x	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y

Release	80x	82x	83x	84x	85x	86x	87x	88x	89x	810x
8.3.x	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y
8.4.x	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y
8.5.x	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y
8.6.x	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y
8.7.x	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y
8.8.x	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y
8.9.x	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y
8.10.x	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y

## Cisco Connected Mobile Experiences Compatibility Matrix

### Important Notes for Connected Mobile Experiences Platform

This section describes Cisco CMX compatibility limitations with the platforms and releases listed in the [Cisco CMX Compatibility Matrix, on page 74](#).

#### General

- We strongly recommend that you upgrade to Cisco CMX Release 10.4.1.x or later if you are running Cisco CMX Release 10.3 or earlier.

#### Cisco High Availability

- The High Availability feature on Cisco CMX:
  - Is supported only in Cisco CMX Release 10.3.x or later.
  - Is supported on all platforms supported by Cisco CMX Release 10.3.x or later.




---

**Note** The Cisco High Availability feature in Cisco CMX Release 10.3.x or later is not supported on the Cisco MSE 3355.

---

- Requires that both primary and standby servers have the same virtual machine size and the same virtual Cisco MSE appliances.

#### Cisco CMX Hyperlocation

- Cisco CMX Release 10.2.x (non-Cisco Hyperlocation apps) is compatible with Cisco Prime Infrastructure Release 2.2.x and 3.0.x.

- Cisco CMX Hyperlocation with the High Availability feature on Cisco CMX requires Cisco Controller Release 8.4.1.210 or later.
- Cisco CMX Hyperlocation requires Cisco Controller Release 8.1.131.0 or later.
- Cisco CMX Hyperlocation is not supported on the Cisco MSE 3355.
- Cisco CMX Hyperlocation is not supported on the Cisco Mobility Express Controllers.

### **Cisco 3375 Appliance for Cisco Connected Mobile Experiences**

- Cisco CMX Release 10.5.1 or later supports the Cisco 3375 Appliance for Cisco Connected Mobile Experiences.

### **Cisco Access Points**

Cisco access points that are supported on Cisco Controllers Release 8.0 up to 8.10 are supported on Cisco CMX.

- Cisco CMX supports Cisco 9166I and 9164I Wi-Fi 6E series access points.
- Cisco CMX supports Cisco 1830, 1840, 1850, 2700, 2800, 3702e, 3702i, 3800, and 4800 access points.
- Cisco CMX supports Catalyst 9105AX, 9115, 9117, 9120AX (with Cisco FastLocate), 9124AX, 9130AXE, 9130AX-E, and 9130AX-I access points.
- (CSCvr26395 and CSCvr26398) The Cisco CMX Location Accuracy Test tool supports only Cisco Hyperlocation-capable access points.

### **Cisco Mobility Express**

- Cisco CMX Release 10.5.0 supports Cisco ME Release 8.8 running on Cisco 1830 and 1850 access points.

### **Cisco Mobility Services Engine 3355 Appliance (physical)**

- Cisco CMX Release 10.4.x or later does not support the Cisco MSE 3355 platform.
- Cisco CMX Release 10.3.x release or earlier are supported on the Cisco MSE 3355 platform. However, the HA feature in Cisco CMX Release 10.3.x is not supported on the Cisco MSE 3355.
- Cisco CMX Release 10.2.x or later is supported on the Cisco MSE 3355 but on a limited scale in terms of number of tracked clients and number of controllers synchronized. Scale numbers for Location and Presence Analytics are documented in the [Cisco Connected Mobile Experiences Data Sheet](#).

### **Cisco Switches**

- Cisco CMX Releases 10.3.1 or later is not compatible with the following Cisco switch platforms:
  - Cisco Catalyst 2960-24TT switch running Cisco Release 15.0(2)SE11
  - Cisco Catalyst 2960-48-PST-L switch running Cisco Release 15.0(2)SE11
  - Cisco Catalyst 2960X-24PS-L switch running Cisco Release 15.2(2)E7



- Cisco Catalyst 3650-24PS switch running Cisco Release 16.3.5b
- Cisco Catalyst 3560-24PS switch running Cisco Release 12.2(55)SE11
- Cisco Catalyst 3850-24XS switch running Cisco Release 16.3.5.b
- Cisco Nexus 5596UP switch running Cisco Release 7.1(4)N1(1)

### Cisco Wireless Controllers

For additional information, see the [Cisco Access Points, on page 72](#) section.

- Cisco CMX Release 10.6.2 and later supports Catalyst 9800-L controller Release 16.12 and later.
- Cisco CMX Release 10.5.1 and later supports Cisco controller Release 8.8.100.
- The Cisco CMX Release 10.5 CMX Grouping feature requires Cisco controller Release 8.7 or later.
- Cisco controller Release 7.x supports the complete set of Cisco CMX Connect services. However:
  - Cisco controller Release 8.2 or later is required to use these features available on Cisco CMX Release 10.2.2: menu link, text link on login page, and DNS-ACL configuration.
  - Cisco controller Release 8.3 or later is required to use the PMS policy uplink bandwidth enforcement feature available on Cisco CMX Release 10.2.2.

## Cisco CMX Compatibility Matrix

Table 12: Cisco CMX Compatibility Matrix<sup>1</sup>

Cisco CMX	Network Management <sup>2,3</sup>	Hardware Platforms <sup>4</sup>	
11.0.0-154	<p data-bbox="636 413 954 447"><b>Cisco Prime Infrastructure<sup>6</sup></b></p> <p data-bbox="636 464 686 491">3.10</p> <p data-bbox="636 512 691 539">3.9.1</p> <p data-bbox="636 560 691 588">3.9.0</p> <p data-bbox="636 609 878 636">3.8.0.310 with patches</p> <p data-bbox="636 657 740 684">3.8.0.310</p> <p data-bbox="636 705 1000 795">3.7.0.159 (with patches for Cisco Catalyst 9800 Controller Releases 16.12.4a and 17.1 and later);</p> <p data-bbox="636 816 691 844">3.7.0</p> <p data-bbox="636 865 760 892">3.6.0.0.172</p> <p data-bbox="636 913 1019 940">3.5.0.0.550 (with Critical Update 02)</p> <p data-bbox="636 961 760 989">3.4.0.0.348</p> <p data-bbox="636 1010 1003 1127"><b>Note</b> We recommend that you use Cisco Prime Infrastructure Release 3.7.0 or later.</p>		

Cisco CMX	Network Management <sup>2,3</sup>	Hardware Platforms <sup>4</sup>	
			<p><b>Cisco Controller</b></p> <p>8.10</p> <p>8.9</p> <p>8.8</p> <p>8.7</p> <p>8.5</p> <p>8.3</p> <p>8.2</p> <p>8.0</p> <p><b>Catalyst 9800 C</b></p> <p>17.11.1</p> <p>17.10.1</p> <p>17.9.3</p> <p>17.9.2</p> <p>17.9.1</p> <p>17.8.1</p> <p>17.7.1</p> <p>17.6.4</p> <p>17.6.3</p> <p>17.6.1 (Non-FIP</p> <p>17.5.1 (Non-FIP</p> <p>17.4.1 (Non-FIP</p> <p>17.3.6</p> <p>17.3.5b</p> <p>17.3.5a</p> <p>17.3.4 (Non-FIP</p> <p>17.3.4c</p> <p>17.3.4</p> <p>17.3.3 (Non-FIP</p> <p>17.3.3</p> <p>17.3.2a (Non-FI</p> <p>17.3.1</p> <p>16.12.5</p>

Cisco CMX	Network Management <sup>2,3</sup>	Hardware Platforms <sup>4</sup>	
			16.12.4a 16.12.3 17.2.1 (Non-FIPS on 17.1.1s 16.12.2s 16.12.1s 16.11.1c 16.11.1b

Cisco CMX	Network Management <sup>2,3</sup>	Hardware Platforms <sup>4</sup>	
10.6.3-146	<p><b>Cisco Prime Infrastructure<sup>6</sup></b></p> <p>3.10</p> <p>3.9.1</p> <p>3.9.0</p> <p>3.8.0.310 with patches</p> <p>3.8.0.310</p> <p>3.7.0.159 (with patches for Cisco Catalyst 9800 Controller Releases 16.12.4a and 17.1 and later);</p> <p>3.7.0</p> <p>3.6.0.0.172</p> <p>3.5.0.0.550 (with Critical Update 02)</p> <p>3.4.0.0.348</p> <p><b>Note</b> We recommend that you use Cisco Prime Infrastructure Release 3.7.0 or later.</p>	<p><b>Cisco CMX</b></p> <p>Cisco 3375 Appliance for CMX</p> <p><b>Cisco MSE</b></p> <p>Cisco MSE 3365 (physical) Appliance</p>	

Cisco CMX	Network Management <sup>2,3</sup>	Hardware Platforms <sup>4</sup>	
			<p><b>Cisco Controller</b><sup>7,8</sup></p> <p>8.10</p> <p>8.9</p> <p>8.8</p> <p>8.7</p> <p>8.5</p> <p>8.3</p> <p>8.2</p> <p>8.0</p> <p><b>Catalyst 9800 Cont</b></p> <p>17.11.1</p> <p>17.10.1</p> <p>17.9.3</p> <p>17.9.2</p> <p>17.9.1</p> <p>17.8.1</p> <p>17.7.1</p> <p>17.6.4</p> <p>17.6.3</p> <p>17.6.1 (Non-FIPS or</p> <p>17.5.1 (Non-FIPS or</p> <p>17.4.1 (Non-FIPS or</p> <p>17.3.6</p> <p>17.3.5b</p> <p>17.3.5a</p> <p>17.3.4 (Non-FIPS or</p> <p>17.3.4c</p> <p>17.3.4</p> <p>17.3.3 (Non-FIPS or</p> <p>17.3.3</p> <p>17.3.2a (Non-FIPS c</p> <p>17.3.1</p> <p>16.12.5</p>

Cisco CMX	Network Management <sup>2,3</sup>	Hardware Platforms <sup>4</sup>	
			16.12.4a 16.12.3 17.2.1 (Non-FIP) 17.1.1s 16.12.2s 16.12.1s 16.11.1c 16.11.1b

Cisco CMX	Network Management <sup>2,3</sup>	Hardware Platforms <sup>4</sup>	
10.6.3-105	<p data-bbox="636 289 959 321"><b>Cisco Prime Infrastructure</b><sup>6</sup></p> <p data-bbox="636 338 688 365">3.10</p> <p data-bbox="636 386 691 413">3.9.1</p> <p data-bbox="636 434 695 462">3.9.0</p> <p data-bbox="636 483 878 510">3.8.0.310 with patches</p> <p data-bbox="636 531 740 558">3.8.0.310</p> <p data-bbox="636 579 1003 669">3.7.0.159 (with patches for Cisco Catalyst 9800 Controller Releases 16.12.4a and 17.1 and later);</p> <p data-bbox="636 690 695 718">3.7.0</p> <p data-bbox="636 739 760 766">3.6.0.0.172</p> <p data-bbox="636 787 1019 814">3.5.0.0.550 (with Critical Update 02)</p> <p data-bbox="636 835 760 863">3.4.0.0.348</p> <p data-bbox="636 884 1008 1003"><b>Note</b> We recommend that you use Cisco Prime Infrastructure Release 3.7.0 or later.</p>	<p data-bbox="1036 289 1170 317"><b>Cisco CMX</b></p> <p data-bbox="1036 338 1382 365">Cisco 3375 Appliance for CMX</p> <p data-bbox="1036 386 1166 413"><b>Cisco MSE</b></p> <p data-bbox="1036 434 1333 495">Cisco MSE 3365 (physical) Appliance</p>	



Cisco CMX	Network Management <sup>2,3</sup>	Hardware Platforms <sup>4</sup>	
			<b>Cisco Controller</b> 8.10 8.9 8.8 8.7 8.5 8.3 8.2 8.0 <b>Catalyst 9800 C</b> 17.9.1 17.8.1 17.7.1 17.6.4 17.6.3 17.6.1 (Non-FIP) 17.5.1 (Non-FIP) 17.4.1 (Non-FIP) 17.3.6 17.3.5b 17.3.5a 17.3.4 (Non-FIP) 17.3.4c 17.3.4 17.3.3 (Non-FIP) 17.3.3 17.3.2a (Non-FIP) 17.3.1 16.12.5 16.12.4a 16.12.3 17.2.1 (Non-FIP) 17.1.1s

Cisco CMX	Network Management <sup>2,3</sup>	Hardware Platforms <sup>4</sup>	
			16.12.2s 16.12.1s 16.11.1c 16.11.1b

Cisco CMX	Network Management <sup>2,3</sup>	Hardware Platforms <sup>4</sup>	
<p>10.6.3-70</p> <p><b>Note</b> For CMX 10.6.3-70 on FIPS to work with 17.x controllers on FIPS, you must install a patch. We are working on the patch, which will be available soon.</p>	<p><b>Cisco Prime Infrastructure</b><sup>6</sup></p> <p>3.10</p> <p>3.9.1</p> <p>3.9.0</p> <p>3.8.0.310 with patches</p> <p>3.8.0.310</p> <p>3.7.0.159 (with patches for Cisco Catalyst 9800 Controller Releases 16.12.4a and 17.1 and later);</p> <p>3.7.0</p> <p>3.6.0.0.172</p> <p>3.5.0.0.550 (with Critical Update 02)</p> <p>3.4.0.0.348</p> <p><b>Note</b> We recommend that you use Cisco Prime Infrastructure Release 3.7.0 or later.</p>	<p><b>Cisco CMX</b></p> <p>Cisco 3375 Appliance for CMX</p> <p><b>Cisco MSE</b></p> <p>Cisco MSE 3365 (physical) Appliance</p>	

Cisco CMX	Network Management <sup>2,3</sup>	Hardware Platforms <sup>4</sup>	
			<p><b>Cisco Controller<sup>7,8</sup></b></p> <p>8.10</p> <p>8.9</p> <p>8.8</p> <p>8.7</p> <p>8.5</p> <p>8.3</p> <p>8.2</p> <p>8.0</p> <p><b>Catalyst 9800 Cont</b></p> <p>17.9.1</p> <p>17.8.1</p> <p>17.7.1</p> <p>17.6.4</p> <p>17.6.3</p> <p>17.6.1 (Non-FIPS or</p> <p>17.5.1 (Non-FIPS or</p> <p>17.4.1 (Non-FIPS or</p> <p>17.3.6</p> <p>17.3.5b</p> <p>17.3.5a</p> <p>17.3.4 (Non-FIPS or</p> <p>17.3.4c</p> <p>17.3.4</p> <p>17.3.3 (Non-FIPS or</p> <p>17.3.3</p> <p>17.3.2a (Non-FIPS c</p> <p>17.3.1</p> <p>16.12.5</p> <p>16.12.4a</p> <p>16.12.3</p> <p>17.2.1 (Non-FIPS or</p> <p>17.1.1s</p>

Cisco CMX	Network Management <sup>2,3</sup>	Hardware Platforms <sup>4</sup>	
			16.12.2s 16.12.1s 16.11.1c 16.11.1b

Cisco CMX	Network Management <sup>2,3</sup>	Hardware Platforms <sup>4</sup>	
10.6.2-89  <b>Note</b> For CMX 10.6.2-89, if FIPS to work with 17.x controllers on FIPS, you must install the <b>cmx-major-patch-10.6.2-1-cmx1</b> patch in CMX.  <b>Note</b> We recommend that you use Cisco Prime Infrastructure Release 3.7.0 or later.	<b>Cisco Prime Infrastructure<sup>6</sup></b>  3.7.1 (with Update 02) 3.7.0 3.6.0.0.172 3.5.0.0.550 (with Critical Update 02) 3.4.0.0.348  <b>Note</b> We recommend that you use Cisco Prime Infrastructure Release 3.7.0 or later.	<b>Cisco CMX</b>  Cisco 3375 Appliance for CMX  <b>Cisco MSE</b>  Cisco MSE 3365 (physical) Appliance	<b>Cisco Controller<sup>7,8</sup></b>  8.10 8.9 8.8 8.7 8.5 8.3 8.2 8.0  <b>Catalyst 9800 Cont</b>  17.6.1 (Non-FIPS or 17.5.1 (Non-FIPS or 17.4.1 (Non-FIPS or 17.3.6 17.3.5b 17.3.5a 17.3.4c 17.3.4 17.3.4 (Non-FIPS or 17.3.3 17.3.2a 17.3.1 17.2.1 (Non-FIPS or 17.1.1s 16.12.5 16.12.4a 16.12.3 16.12.2s 16.12.1s 16.11.1c 16.11.1b

Cisco CMX	Network Management <sup>2,3</sup>	Hardware Platforms <sup>4</sup>	
10.6.2-72	<p data-bbox="675 289 992 321"><b>Cisco Prime Infrastructure<sup>6</sup></b></p> <p data-bbox="675 338 776 365">3.8.0.310</p> <p data-bbox="675 386 919 417">3.7.1 (with Update 02)</p> <p data-bbox="675 436 1029 527">3.7.0.159 (with patches for Cisco Catalyst 9800 Controller Release 17.1 and later)</p> <p data-bbox="675 546 732 573">3.7.0</p> <p data-bbox="675 592 797 619">3.6.0.0.172</p> <p data-bbox="675 638 1057 669">3.5.0.0.550 (with Critical Update 02)</p> <p data-bbox="675 688 797 716">3.4.0.0.348</p> <p data-bbox="675 735 1040 858"><b>Note</b> We recommend that you use Cisco Prime Infrastructure Release 3.7.0 or later.</p>	<p data-bbox="1073 289 1208 321"><b>Cisco CMX</b></p> <p data-bbox="1073 338 1414 369">Cisco 3375 Appliance for CMX</p> <p data-bbox="1073 386 1203 417"><b>Cisco MSE</b></p> <p data-bbox="1073 436 1365 495">Cisco MSE 3365 (physical) Appliance</p>	<p data-bbox="1446 289 1624 321"><b>Cisco Controller</b></p> <p data-bbox="1446 338 1495 365">8.10</p> <p data-bbox="1446 386 1479 413">8.9</p> <p data-bbox="1446 432 1479 459">8.8</p> <p data-bbox="1446 478 1479 506">8.7</p> <p data-bbox="1446 525 1479 552">8.5</p> <p data-bbox="1446 571 1479 598">8.3</p> <p data-bbox="1446 617 1479 644">8.2</p> <p data-bbox="1446 663 1479 690">8.0</p> <p data-bbox="1446 709 1624 741"><b>Catalyst 9800 C</b></p> <p data-bbox="1446 760 1528 787">17.3.4c</p> <p data-bbox="1446 806 1511 833">17.3.4</p> <p data-bbox="1446 852 1511 879">17.3.3</p> <p data-bbox="1446 898 1528 926">17.3.2a</p> <p data-bbox="1446 945 1511 972">17.3.1</p> <p data-bbox="1446 991 1528 1018">17.1.1s</p> <p data-bbox="1446 1037 1528 1064">16.12.2s</p> <p data-bbox="1446 1083 1528 1110">16.12.1s</p> <p data-bbox="1446 1129 1528 1157">16.11.1c</p> <p data-bbox="1446 1176 1528 1203">16.11.1b</p>

Cisco CMX	Network Management <sup>2,3</sup>	Hardware Platforms <sup>4</sup>	
10.6.2	<p data-bbox="636 289 954 323"><b>Cisco Prime Infrastructure<sup>6</sup></b></p> <p data-bbox="636 340 695 373">3.7.0</p> <p data-bbox="636 390 760 424">3.6.0.0.172</p> <p data-bbox="636 441 1019 474">3.5.0.0.550 (with Critical Update 02)</p> <p data-bbox="636 491 760 525">3.4.0.0.348</p> <p data-bbox="636 541 1006 659"><b>Note</b> We recommend that you use Cisco Prime Infrastructure Release 3.7.0 or later.</p>	<p data-bbox="1034 289 1170 323"><b>Cisco CMX</b></p> <p data-bbox="1034 340 1382 373">Cisco 3375 Appliance for CMX</p> <p data-bbox="1034 390 1162 424"><b>Cisco MSE</b></p> <p data-bbox="1034 441 1333 499">Cisco MSE 3365 (physical) Appliance</p>	<p data-bbox="1404 289 1620 323"><b>Cisco Controller<sup>7,8</sup></b></p> <p data-bbox="1404 340 1458 373">8.10</p> <p data-bbox="1404 390 1446 424">8.9</p> <p data-bbox="1404 441 1446 474">8.8</p> <p data-bbox="1404 491 1446 525">8.7</p> <p data-bbox="1404 541 1446 575">8.5</p> <p data-bbox="1404 592 1446 625">8.3</p> <p data-bbox="1404 642 1446 676">8.2</p> <p data-bbox="1404 693 1446 726">8.0</p> <p data-bbox="1404 743 1624 777"><b>Catalyst 9800 Cont</b></p> <p data-bbox="1404 793 1490 827">17.3.4c</p> <p data-bbox="1404 844 1479 877">17.3.4</p> <p data-bbox="1404 894 1479 928">17.3.3</p> <p data-bbox="1404 945 1490 978">17.3.2a</p> <p data-bbox="1404 995 1479 1029">17.3.1</p> <p data-bbox="1404 1045 1507 1079">16.12.1s</p> <p data-bbox="1404 1096 1507 1129">16.11.1c</p> <p data-bbox="1404 1146 1507 1180">16.11.1b</p>



Cisco CMX	Network Management <sup>2,3</sup>	Hardware Platforms <sup>4</sup>	
10.6.1	<b>Cisco Prime Infrastructure<sup>6</sup></b> 3.6.0.0.172 3.5.0.0.550 (with Critical Update 02) 3.4.0.0.348	<b>Cisco CMX</b> Cisco 3375 Appliance for CMX  <b>Cisco MSE</b> Cisco MSE 3365 (physical) Appliance	<b>Cisco Controller</b> 8.9 8.8 8.7 8.5 8.3 8.2 8.0  <b>Catalyst 9800 C</b> 17.3.4c 17.3.4 17.3.3 17.3.2a 17.3.1 16.11.1b 16.10.1e
10.6.0	<b>Cisco Prime Infrastructure<sup>6</sup></b> 3.5.0.0.550 (with Critical Update 02) 3.4.0.0.348	<b>Cisco CMX</b> Cisco 3375 Appliance for CMX  <b>Cisco MSE</b> Cisco MSE 3365 (physical) Appliance	<b>Cisco Controller</b> 8.9 8.8 8.7 8.5 8.3 8.2 8.0  <b>Catalyst 9800 C</b> 17.3.4c 17.3.4 17.3.3 17.3.2a 17.3.1 16.10.1e

Cisco CMX	Network Management <sup>2,3</sup>	Hardware Platforms <sup>4</sup>	
10.5.1	<b>Cisco Prime Infrastructure<sup>6</sup></b> 3.4.0.0.348 3.3.0.0.342 3.2.0.0.258	<b>Cisco CMX</b> Cisco 3375 Appliance for CMX  <b>Cisco MSE</b> Cisco MSE 3365 (physical) Appliance	<b>Cisco Controller<sup>7,8</sup></b> 8.8 8.7 8.5 8.3 8.2 8.0 <b>Catalyst 9800 Cont</b> 17.3.4c 17.3.4 17.3.3 17.3.2a 17.3.1 16.10.1
10.5.0	<b>Cisco Prime Infrastructure<sup>6</sup></b> 3.4.0.0.348 3.3.0.0.342 3.2.0.0.258	<b>Cisco MSE</b> Cisco MSE 3365 (physical) Appliance	<b>Cisco Controller<sup>7,8</sup></b> 8.7 8.5 8.3 8.2 8.0
10.4.x	<b>Cisco Prime Infrastructure<sup>6</sup></b> 3.3.0.0.342 3.2.0.0.258 3.1.0.0.132	<b>Cisco MSE</b> Cisco MSE 3365 (physical) Appliance	<b>Cisco Controller<sup>7,8</sup></b> 8.6 8.5 8.3 8.2 8.0
10.3.x	<b>Cisco Prime Infrastructure<sup>6</sup></b> 3.0 to 3.2 2.2	<b>Cisco MSE</b> Cisco MSE 3365 (physical) Appliance  Cisco MSE 3355 (physical) Appliance	<b>Cisco Controller<sup>7,8</sup></b> 8.5 8.3 8.2 8.0

1	For Cisco CMX compatibility limitations, see the <a href="#">Important Notes for Connected Mobile Experiences Platform</a> section.
2	Cisco DNA Center Release 2.1.2.x or later supports Cisco CMX Release 10.6.2, 10.6.3 or later.  For Cisco DNA Center compatibility information, see the Cisco Digital Network Architecture Center Supported Devices matrix and the Cisco Software-Defined Access Hardware and Software Compatibility Matrix matrix.
3	Cisco CMX Release 10.6.0 and later is required to support Cisco DNA Spaces. For complete Cisco DNA Spaces compatibility information, see the <b>Prerequisites</b> chapter of the <i>Cisco DNA Spaces Configuration Guide</i> and the <b>Product Overview</b> chapter of the <i>Cisco DNA Spaces: Connector Configuration Guide</i> .
4	For Cisco Mobility Express Solution compatibility information, see the <a href="#">Cisco Mobility Express Solution Compatibility Matrix</a> section.
5	For Cisco Embedded Wireless Controller on Catalyst Access Points compatibility information, see the <a href="#">Cisco Embedded Wireless Controller Matrix</a> section.
6	For Cisco Prime Infrastructure compatibility information, see the <a href="#">Cisco Prime Infrastructure Compatibility Matrix</a> section in the <i>Compatibility Matrix for Legacy Cisco Wireless Solutions</i> document.
7	For Cisco Controller Release 8.x releases, we recommend that you install the latest maintenance release that corresponds to your software version.
8	For Cisco Controller and Cisco AP compatibility information, see the <a href="#">Supported Access Points in Cisco Catalyst 9800 Series Wireless Controller Software Releases</a> section.
9	For CMX 10.6.2-89 on FIPS to work with 17.x controllers on FIPS, you must install the <b>cmx-major-patch-10.6.2-1.cmxp</b> patch in CMX. This patch for <a href="#">CSCvx23734</a> is available on request and provides: <ul style="list-style-type: none"> <li>• CMX on FIPS and 17.x controllers on FIPS.</li> <li>• CMX on non-FIPS and 17.x controllers on FIPS.</li> </ul>

## Cisco Prime Infrastructure Compatibility Matrix

### Cisco Prime Infrastructure and Cisco Wireless Release Compatibility Matrix

Table 13: [Cisco Prime Infrastructure and Cisco Wireless Release Compatibility Matrix](#), on page 93 lists the Cisco Controller releases and Identity Services Engine (ISE) versions that are compatible with the Cisco Prime Infrastructure releases.

For information about wireless device support in Cisco Prime Infrastructure, see the following URL:  
<https://www.cisco.com/c/en/us/support/cloud-systems-management/prime-infrastructure/products-device-support-tables-list.html>

**Note**

- 
- For Cisco CMX and Cisco MSE compatibility details, see the [Cisco Connected Mobile Experiences Compatibility Matrix](#), and the [Cisco Mobility Services Engine Compatibility Matrix](#) respectively.
  - For Cisco MSE compatibility with Cisco Prime Infrastructure releases, see the applicable Cisco Prime Infrastructure release notes at: <https://www.cisco.com/c/en/us/support/cloud-systems-management/prime-infrastructure/products-release-notes-list.html>.
-

Table 13: Cisco Prime Infrastructure and Cisco Wireless Release Compatibility Matrix

Cisco Prime Infrastructure	Cisco Controller	ISE	Remarks
3.10.4		2.7	Cisco Prime Infrastructure release might not be supported for older controller versions < 8.5, however, it is recommended to use Cisco Controller versions 8.5 and above.
3.10.3		2.6	
3.10.2		2.4	
3.10.1		2.3	
3.10		2.2	
3.9.1		2.1	
3.9		2.0	
3.8.1		1.4	
3.8		1.3	
			<p>Cisco Prime Infrastructure release might not be supported for older controller versions &lt; 8.5, however, it is recommended to use Cisco Controller versions 8.5 and above.</p> <p>Cisco Prime Infrastructure release 3.8 does not support Catalyst 9800 Controller releases 16.12 and above.</p>

Cisco Prime Infrastructure	Cisco Controller	ISE	Remarks
	8.10.185.0		
	8.10.183.0		
	8.10.182.0		
	8.10.181.0		
	8.10.171.0		
	8.10.162.0		
	8.10.151.0		
	8.10.142.0		
	8.10.130.0		
	8.10.122.0		
	8.10.121.0		
	8.10.113.0		
	8.10.112.0		
	8.10.105.0		
	8.9.111.0		
	8.9.100.0		
	8.8.130.0		
	8.8.125.0		
	8.8.120.0		
	8.8.111.0		
	8.8.100.0		
	8.7.106.0		
	8.7.102.0		
	8.6.101.0		
	8.5.182.0		
	8.5.171.0		
	8.5.164.0		
	8.5.161.0		
	8.5.160.0		
	8.5.151.0		
	8.5.140.0		
	8.5.135.0		

Cisco Prime Infrastructure	Cisco Controller	ISE	Remarks
	8.5.131.0 8.5.120.0 8.5.110.0 8.5.105.0 8.5.103.0		

Cisco Prime Infrastructure	Cisco Controller	ISE	Remarks
3.7.1	8.10.130.0	2.7	Cisco Prime Infrastructure release might not be compatible for older controller versions < 8.5, however recommended to use Cisco Controller version 8.5 and above.
	8.10.122.0	2.6	
	8.10.121.0	2.4	
	8.10.113.0	2.3	
	8.10.112.0	2.2	
	8.10.105.0	2.1	
	8.9.111.0	2.0	
	8.9.100.0	1.4	
	8.8.130.0	1.3	
	8.8.125.0		
	8.8.120.0		
	8.8.111.0		
	8.8.100.0		
	8.7.106.0		
	8.7.102.0		
	8.6.101.0		
	8.5.182.0		
	8.5.171.0		
	8.5.164.0		
	8.5.161.0		
	8.5.160.0		
	8.5.151.0		
	8.5.140.0		
	8.5.135.0		
	8.5.131.0		
	8.5.120.0		
	8.5.110.0		
8.5.105.0			
8.5.103.0			



Cisco Prime Infrastructure	Cisco Controller	ISE	Remarks
3.7	8.10.130.0 8.10.122.0 8.10.121.0 8.10.113.0 8.10.112.0 8.10.105.0 8.9.111.0 8.9.100.0 8.8.130.0 8.8.125.0 8.8.120.0 8.8.111.0 8.8.100.0 8.7.106.0 8.7.102.0 8.6.101.0 8.5.182.0 8.5.171.0 8.5.164.0 8.5.161.0 8.5.160.0 8.5.151.0 8.5.140.0 8.5.135.0 8.5.131.0 8.5.120.0 8.5.110.0 8.5.105.0 8.5.103.0	2.6 2.4 2.3 2.2 2.1 2.0 1.4 1.3	Cisco Prime Infrastructure release might not be compatible with older controller versions < 8.5, however, it is recommended to use Cisco Controller versions 8.5 and above.

Cisco Prime Infrastructure	Cisco Controller	ISE	Remarks
3.6	8.9.111.0	2.6	—
	8.9.100.0	2.4	
	8.8.130.0	2.3	
	8.8.125.0	2.2	
	8.8.120.0	2.1	
	8.8.111.0	2.0	
	8.8.100.0	1.4	
	8.7.106.0	1.3	
	8.7.102.0		
	8.6.101.0		
	8.5.182.0		
	8.5.171.0		
	8.5.164.0		
	8.5.161.0		
	8.5.160.0		
	8.5.151.0		
	8.5.140.0		
	8.5.135.0		
	8.5.131.0		
	8.5.120.0		
	8.5.110.0		
	8.5.105.0		
	8.5.103.0		

Cisco Prime Infrastructure	Cisco Controller	ISE	Remarks
3.5	8.8.130.0	2.4	—
	8.8.125.0	2.3	
	8.8.120.0	2.2	
	8.8.111.0	2.1	
	8.8.100.0	2.0	
	8.7.106.0	1.4	
	8.7.102.0	1.3	
	8.6.101.0		
	8.5.182.0		
	8.5.171.0		
	8.5.164.0		
	8.5.161.0		
	8.5.160.0		
	8.5.151.0		
	8.5.140.0		
	8.5.135.0		
	8.5.131.0		
	8.5.120.0		
	8.5.110.0		
	8.5.105.0		
8.5.103.0			

## Cisco Prime Infrastructure, Cisco Catalyst 9800 Series Wireless Controllers and Cisco Converged Access Solution Compatibility Matrix

[Cisco Prime Infrastructure, Cisco Catalyst 9800 Series Wireless Controllers and Cisco Converged Access Solution Compatibility Matrix, on page 99](#) lists the Cisco IOS/IOS XE releases and the corresponding devices that are compatible with the Cisco Prime Infrastructure releases.

Table 14: Cisco Prime Infrastructure and Cisco IOS/IOS XE Release Compatibility Matrix

Cisco Prime Infrastructure	Cisco IOS/IOS XE Release	Device	Remarks
3.10.4	Current Release with N-2 supported	Dublin 17.11.1 Dublin 17.10.1 Cupertino 17.9.3 Cupertino 17.9.2 Cupertino 17.9.1 Cupertino 17.8.1 Cupertino 17.7.1 Bengaluru 17.6.4	Cisco Catalyst 9800-40 Wireless Controller Cisco Catalyst 9800-80 Wireless Controller Cisco Catalyst 9800-L-F Wireless Controller Cisco Catalyst 9800-CL Wireless Controller for Cloud  <b>Note:</b> Cisco Prime Infrastructure do not support Cisco IOS/IOS 16.10.
3.10.3	Current Release with N-2 supported	Dublin 17.10.1 Cupertino 17.9.3 Cupertino 17.9.2 Cupertino 17.9.1 Cupertino 17.8.1 Cupertino 17.7.1 Bengaluru 17.6.4	Cisco Catalyst 9800-40 Wireless Controller Cisco Catalyst 9800-80 Wireless Controller Cisco Catalyst 9800-L-F Wireless Controller Cisco Catalyst 9800-CL Wireless Controller for Cloud  <b>Note:</b> Cisco Prime Infrastructure do not support Cisco IOS/IOS 16.10.
3.10.2	Current Release with N-2 supported	Cupertino 17.9.3 Cupertino 17.9.2 Cupertino 17.9.1 Cupertino 17.8.1 Cupertino 17.7.1 Bengaluru 17.6.4	Cisco Catalyst 9800-40 Wireless Controller Cisco Catalyst 9800-80 Wireless Controller Cisco Catalyst 9800-L-F Wireless Controller Cisco Catalyst 9800-CL Wireless Controller for Cloud  <b>Note:</b> Cisco Prime Infrastructure do not support Cisco IOS/IOS 16.10.
3.10.1	Current Release with N-2 supported	Cupertino 17.8.1 Cupertino 17.7.1 Bengaluru 17.6.3 Bengaluru 17.6.4 Amsterdam 17.3.5a	Cisco Catalyst 9800-40 Wireless Controller Cisco Catalyst 9800-80 Wireless Controller Cisco Catalyst 9800-L-F Wireless Controller Cisco Catalyst 9800-CL Wireless Controller for Cloud  <b>Note:</b> Cisco Prime Infrastructure do not support Cisco IOS/IOS 16.10.

Cisco Prime Infrastructure	Cisco IOS/IOS XE Release		Device	Remarks
3.10	Current Release with N-2 supported	Bengaluru 17.6.x	Cisco Catalyst 9800-40 Wireless Controller	Cisco Prime Infrastructure support Cisco IOS XE Gibraltar 16.11 and 16.10.  For instructions to enable Cisco Prime Infrastructure support for Cisco IOS/IOS XE releases, see the Enable Backward Compatibility section in the latest <i>Cisco Prime Infrastructure</i> release notes.  <b>Note:</b> Cisco Prime Infrastructure does not support Cisco IOS/IOS XE releases 16.10.
		Bengaluru 17.5.1	Cisco Catalyst 9800-80 Wireless Controller	
		Bengaluru 17.4.1		
3.9.1	Current Release with N-2 supported	Bengaluru 17.5.1	Cisco Catalyst 9800-L-F Wireless Controller	
		Bengaluru 17.4.1	Cisco Catalyst 9800-CL Wireless Controller for Cloud	
		Amsterdam 17.3.x		
3.9	Current Release with N-2 supported	Bengaluru 17.4.1		
		Amsterdam 17.3.x		
		Amsterdam 17.2		
3.8.1	Current Release with N-2 supported	Amsterdam 17.3.x	Cisco Catalyst 9800-40 Wireless Controller	Cisco Prime Infrastructure support Cisco IOS/IOS XE Gibraltar 16.11 and 16.10.
		Amsterdam 17.2	Cisco Catalyst 9800-80 Wireless Controller	
		Amsterdam 17.1	Cisco Catalyst 9800-L-F Wireless Controller Cisco Catalyst 9800-CL Wireless Controller for Cloud	
3.8	Current Release with N-2 supported	Amsterdam 17.2.1	Cisco Catalyst 9800-40 Wireless Controller	Cisco Prime Infrastructure support Cisco IOS/IOS XE Releases 16.11 and 16.10.
		Amsterdam 17.1	Cisco Catalyst 9800-80 Wireless Controller	
			Cisco Catalyst 9800-L-F Wireless Controller Cisco Catalyst 9800-CL Wireless Controller for Cloud	
3.7.1	Current Release with N-2 supported	Amsterdam 17.1	Cisco Catalyst 9800-40 Wireless Controller	—
		Gibraltar 16.12.x	Cisco Catalyst 9800-80 Wireless Controller	
		Gibraltar 16.11	Cisco Catalyst 9800-L-F Wireless Controller Cisco Catalyst 9800-CL Wireless Controller for Cloud.	

Cisco Prime Infrastructure	Cisco IOS/IOS XE Release		Device	Remarks
3.7	Current Release	Gibraltar 16.12.x Gibraltar 16.11 Gibraltar 16.10	Cisco Catalyst 9800-40 Wireless Controller  Cisco Catalyst 9800-80 Wireless Controller  Cisco Catalyst 9800-L-F Wireless Controller  Cisco Catalyst 9800-CL Wireless Controller for Cloud.	—
3.6	Current Release	Gibraltar 16.10 Gibraltar 16.11 Gibraltar 16.9	Cisco Catalyst 9800-CL Wireless Controller for Cloud  Cisco Catalyst 9800-40 Wireless Controller	—
3.5	Current Release	Gibraltar 16.9 Gibraltar 16.10  Denali 16.3.3 Denali 16.3.2 Denali 16.3.1	Cisco Catalyst 9800-CL Wireless Controller for Cloud  Cisco Catalyst 9800-40 Wireless Controller	—

## Cisco Mobility Services Engine Compatibility Matrix

Information in this section cites cross-platform compatibility testing performed from only the Cisco MSE perspective and is limited to up to specific product releases cited in this section.

For Cisco MSE compatibility with product releases not cited in this section, see the compatibility matrix for the relevant product. For example, for the most recent compatibility information between Cisco CMX and Cisco MSE, see the [Cisco CMX Compatibility Matrix, on page 74](#).

### Important Notes

Information in this section cites cross-platform compatibility testing performed from only the Cisco MSE perspective and is limited to up to specific product releases cited in this section.

For Cisco MSE compatibility with product releases not cited in this section, see the compatibility matrix for the relevant product. For example, for the most recent compatibility information between Cisco CMX and Cisco MSE, see the [Cisco CMX Compatibility Matrix, on page 74](#).

For Cisco MSE compatibility with Cisco Prime Infrastructure releases, see the applicable [Cisco Prime Infrastructure release notes](#).

#### General:

- ISE 2.x or ISE 1.4 only works with Cisco MSE Release 8.0 or earlier.

- Cisco MSE release 7.5 or later is not bundled with AeroScout CLE. However, AeroScout CLE is compatible with Cisco MSE Release 7.5 or later, which uses the API interface.
- This compatibility matrix lists only the compatibility information of Cisco MSE with other Cisco wireless products. This matrix does not reflect compatibility information between Cisco Controller and Cisco Prime Infrastructure or Cisco NCS. For compatibility information about Cisco Prime Infrastructure with Cisco Controller and other wireless products, see the *Cisco Prime Infrastructure Release Notes*.
- For information about the Cisco Connected Mobile Experiences (CMX) 10.x solution compatibility matrix, see the [Cisco Connected Mobile Experiences Compatibility Matrix, on page 71](#) section.

### Cisco Prime Infrastructure

- Cisco MSE Release 8.0.140.x or later is compatible with Cisco Prime Infrastructure Releases 3.1.7, 3.1.6, 3.1.5, 3.1.3, 3.1.1, 3.0.3.1, and 2.2.3.5. If you encounter reachability issues with the Cisco MSE, upgrade to Prime Infrastructure Release 3.1.3. (CSCuz19013)
- For Cisco MSE Release 8.0.x HA and Controller Release 8.0 or later, Prime Infrastructure Release 2.2.x is compatible.
- Cisco MSE 3365 supports Cisco Prime Infrastructure 2.1.1 or later. Cisco MSE 3365 does not support Cisco Prime Infrastructure 2.1.0.

### Cisco Access Points

- Cisco MSE Release 8.0.140.9 and later includes wIPS and CAS support for the Cisco Aironet 1800, 2800, 3800, and 4800 series.

### Catalyst Switches

- Cisco MSE platforms running Cisco MSE Release 8.x are not compatible with the following Cisco switch platforms:
  - Cisco Catalyst 2960-24TT switch running Cisco Release 15.0(2)SE11
  - Cisco Catalyst 2960-48-PST-L switch running Cisco Release 15.0(2)SE11
  - Cisco Catalyst 2960X-24PS-L switch running Cisco Release 15.2(2)E7
  - Cisco Catalyst 3650-24PS switch running Cisco Release 16.3.5b
  - Cisco Catalyst 3560-24PS switch running Cisco Release 12.2(55)SE11
  - Cisco Catalyst 3850-24XS switch running Cisco Release 16.3.5.b
  - Cisco Nexus 5596UP switch running Cisco Release 7.1(4)N1(1)

## Cisco MSE Compatibility Matrix for Software Versions 7.5.x through 8.x

Information in this section cites cross-platform compatibility testing performed from only the Cisco MSE perspective and is limited to up to specific product releases cited in this section.

For Cisco MSE compatibility with product releases not cited in this section, see the compatibility matrix for the relevant product. For example, for the most recent compatibility information between Cisco CMX and Cisco MSE, see the [Cisco CMX Compatibility Matrix, on page 74](#) section.

For Cisco MSE compatibility with Cisco Prime Infrastructure releases, see the applicable [Cisco Prime Infrastructure release notes](#).



Table 15: Cisco MSE Compatibility Matrix for Software Versions 7.5.x through 8.x

MSE 3355	MSE 3365	MSE Virtual Appliance	Prime Infrastructure	Controller	Converge
8.0.150.x	8.0.150.x	8.0.150.x	3.9.1		3.7.x
			3.8.x		3.6.x
			3.7.x		3.3.5
			3.6.x		3.3.4
			3.5.x		3.3.3
			3.4.x		3.3.2
			3.3.1		3.3.0
			3.3		3.2.3
			3.2.2		3.2.2
			3.2.1		3.2.0
			3.2		3.1.6
			3.1.7		
			3.1.6		
			3.1.5		
			3.1.3		
			3.1		
			3.0.3		
			2.2.3		

MSE 3355	MSE 3365	MSE Virtual Appliance	Prime Infrastructure	Controller	Converged A
				8.5.12x.0 8.5.11x.0 8.5.10x.0 8.4.10x.0 8.3.14x.0 8.3.13x.0 8.3.12x.0 8.3.112.0 8.3.111.0 8.3.102.0 8.2.16x.0 8.2.160.0 8.2.151.0 8.2.141.0 8.2.130.0 8.2.121.0 8.2.111.0 8.2.110.0 8.1.131.0 8.1.122.0 8.1.111.0 8.1.102.0 8.0.15x.0 8.0.140.0 8.0.13x.0 8.0.121.0 8.0.120.0 8.0.110.0 8.0.100.0 7.6.130.0* 7.6.120.0* 7.6.110.0*	

MSE 3355	MSE 3365	MSE Virtual Appliance	Prime Infrastructure	Controller	Converge
				7.6.100.0* 7.5.102.0** 7.4.121.0** 7.4.110.0** 7.4.100.60** 7.4.100.0** 7.3.112.0** 7.3.101.0** 7.2.111.3** 7.2.110.0** 7.2.103.0** 7.0.240.0** 7.0.235.3** 7.0.235.0** 7.0.230.0** 7.1.91.0** 7.0.220.0** 7.0.116.0** 7.0.98.218** 7.0.98.0**	

MSE 3355	MSE 3365	MSE Virtual Appliance	Prime Infrastructure	Controller	Converged A
8.0.140.x	8.0.140.x	8.0.140.x	3.4.x 3.3.1 3.3 3.2.2 3.2.1 3.2 3.1.7 3.1.6 3.1.5 3.1.3 3.1 3.0.3 2.2.3		3.7.x 3.6.x 3.3.5 3.3.4 3.3.3 3.3.2 3.3.0 3.2.3 3.2.2 3.2.0 3.1.6

MSE 3355	MSE 3365	MSE Virtual Appliance	Prime Infrastructure	Controller	Converge
				8.5.12x.0 8.5.11x.0 8.5.10x.0 8.4.10x.0 8.3.14x.0 8.3.13x.0 8.3.12x.0 8.3.112.0 8.3.111.0 8.3.102.0 8.2.16x.0 8.2.160.0 8.2.151.0 8.2.141.0 8.2.130.0 8.2.121.0 8.2.111.0 8.2.110.0 8.1.131.0 8.1.122.0 8.1.111.0 8.1.102.0 8.0.15x.0 8.0.140.0 8.0.13x.0 8.0.121.0 8.0.120.0 8.0.110.0 8.0.100.0 7.6.130.0* 7.6.120.0* 7.6.110.0*	

MSE 3355	MSE 3365	MSE Virtual Appliance	Prime Infrastructure	Controller	Converged A
				7.6.100.0* 7.5.102.0** 7.4.121.0** 7.4.110.0** 7.4.100.60** 7.4.100.0** 7.3.112.0** 7.3.101.0** 7.2.111.3** 7.2.110.0** 7.2.103.0** 7.0.240.0** 7.0.235.3** 7.0.235.0** 7.0.230.0** 7.1.91.0** 7.0.220.0** 7.0.116.0** 7.0.98.218** 7.0.98.0**	

<b>MSE 3355</b>	<b>MSE 3365</b>	<b>MSE Virtual Appliance</b>	<b>Prime Infrastructure</b>	<b>Controller</b>	<b>Converge</b>
8.0.130.0	8.0.130.0	8.0.130.0	3.1 3.0.1 3.0 2.2 and later 1.4***		3.7.x 3.6.x 3.3.5 3.3.4 3.3.3 3.3.2 3.2.3 3.2.2

MSE 3355	MSE 3365	MSE Virtual Appliance	Prime Infrastructure	Controller	Converged A
				8.3.13x.0 8.3.111.0 8.3.102.0 8.2.16x.0 8.2.151.0 8.2.141.0 8.2.130.0 8.2.121.0 8.2.111.0 8.2.110.0 8.1.131.0 8.1.122.0 8.1.111.0 8.1.102.0 8.0.15x.0 8.0.140.0 8.0.13x.0 8.0.121.0 8.0.120.0 8.0.110.0 8.0.100.0 7.6.130.0* 7.6.120.0* 7.6.110.0* 7.6.100.0* 7.5.102.0** 7.4.121.0** 7.4.110.0** 7.4.100.60** 7.4.100.0** 7.3.112.0** 7.3.101.0**	



MSE 3355	MSE 3365	MSE Virtual Appliance	Prime Infrastructure	Controller	Converge
				7.2.111.3** 7.2.110.0** 7.2.103.0** 7.0.240.0** 7.0.235.3** 7.0.235.0** 7.0.230.0** 7.1.91.0** 7.0.220.0** 7.0.116.0** 7.0.98.218** 7.0.98.0**	

MSE 3355	MSE 3365	MSE Virtual Appliance	Prime Infrastructure	Controller	Converged A
8.0.120.7	8.0.120.7	8.0.120.7	3.0.1 3.0 2.2.2*** 2.2.1 2.2 2.1.2*** 2.1.1*** 1.4*****		3.7.x 3.6.x 3.3.5 3.3.4 3.3.3 3.3.2 3.2.3 3.2.2

MSE 3355	MSE 3365	MSE Virtual Appliance	Prime Infrastructure	Controller	Converge
				8.1.131.0	
				8.1.122.0	
				8.1.111.0	
				8.1.102.0	
				8.0.15x.0	
				8.0.140.0	
				8.0.13x.0	
				8.0.121.0	
				8.0.120.0	
				8.0.110.0	
				8.0.100.0	
				7.6.130.0	
				7.6.120.0	
				7.6.110.0*	
				7.6.100.0*	
				7.5.102.0****	
				7.4.150.0****	
				7.4.140.0****	
				7.4.130.0****	
				7.4.121.0****	
				7.4.110.0****	
				7.4.100.60****	
				7.4.100.0****	
				7.3.112.0****	
				7.3.101.0****	
				7.2.111.3****	
				7.2.110.0****	
				7.2.103.0****	
				7.0.240.0****	
				7.0.235.3****	
				7.0.235.0****	
				7.0.230.0****	

MSE 3355	MSE 3365	MSE Virtual Appliance	Prime Infrastructure	Controller	Converged A
				7.1.91.0**** 7.0.220.0**** 7.0.116.0**** 7.0.98.218**** 7.0.98.0****	

MSE 3355	MSE 3365	MSE Virtual Appliance	Prime Infrastructure	Controller	Converge
8.0.120.0	8.0.120.0	8.0.120.0	3.0.1 3.0 2.2.2*** 2.2.1 2.2 2.1.2*** 2.1.1*** 1.4*****		3.7.x 3.6.x 3.3.5 3.3.4 3.3.3 3.3.2 3.2.3 3.2.2

MSE 3355	MSE 3365	MSE Virtual Appliance	Prime Infrastructure	Controller	Converged A
				8.1.131.0	
				8.1.122.0	
				8.1.111.0	
				8.1.102.0	
				8.0.15x.0	
				8.0.140.0	
				8.0.13x.0	
				8.0.121.0	
				8.0.120.0	
				8.0.110.0	
				8.0.100.0	
				7.6.130.0	
				7.6.120.0	
				7.6.110.0*	
				7.6.100.0*	
				7.5.102.0****	
				7.4.150.0****	
				7.4.140.0****	
				7.4.130.0****	
				7.4.121.0****	
				7.4.110.0****	
				7.4.100.60****	
				7.4.100.0****	
				7.3.112.0****	
				7.3.101.0****	
				7.2.111.3****	
				7.2.110.0****	
				7.2.103.0****	
				7.0.240.0****	
				7.0.235.3****	
				7.0.235.0****	
				7.0.230.0****	

MSE 3355	MSE 3365	MSE Virtual Appliance	Prime Infrastructure	Controller	Converge
				7.1.91.0**** 7.0.220.0**** 7.0.116.0**** 7.0.98.218**** 7.0.98.0****	

MSE 3355	MSE 3365	MSE Virtual Appliance	Prime Infrastructure	Controller	Converged A
8.0.110.0	—	8.0.110.0	2.2.1 2.2 2.1.2*** 2.1.1*** 2.1*** 2.0*** 1.4*****		3.7.x 3.6.x 3.3.x 3.2.x



MSE 3355	MSE 3365	MSE Virtual Appliance	Prime Infrastructure	Controller	Converge
				8.1.131.0	
				8.1.122.0	
				8.1.111.0	
				8.1.102.0	
				8.0.15x.0	
				8.0.140.0	
				8.0.13x.0	
				8.0.121.0	
				8.0.120.0	
				8.0.115.0	
				8.0.110.0	
				8.0.100.0	
				7.6.130.0	
				7.6.120.0	
				7.6.110.0*	
				7.6.100.0*	
				7.5.102.0****	
				7.4.150.0****	
				7.4.140.0****	
				7.4.130.0****	
				7.4.121.0****	
				7.4.110.0****	
				7.4.100.60****	
				7.4.100.0****	
				7.3.112.0****	
				7.3.101.0****	
				7.2.111.3****	
				7.2.110.0****	
				7.2.103.0****	
				7.0.240.0****	
				7.0.235.3****	
				7.0.235.0****	

MSE 3355	MSE 3365	MSE Virtual Appliance	Prime Infrastructure	Controller	Converged A
				7.0.230.0**** 7.1.91.0**** 7.0.220.0**** 7.0.116.0**** 7.0.98.218**** 7.0.98.0**** 7.0.250.0 7.0.251.0 7.0.252.0	

MSE 3355	MSE 3365	MSE Virtual Appliance	Prime Infrastructure	Controller	Converge
8.0.100.0*	—	8.0.100.0	2.2.1	8.1.131.0	3.7.x
			2.2	8.1.122.0	3.6.x
			2.1.2	8.1.111.0	3.3.5
			2.1.1***	8.1.102.0	3.3.4
			2.1	8.0.100.0	3.3.3
			2.0	7.6.130.0	3.3.2
			1.4*****	7.6.120.0	3.2.3
				7.6.110.0*	3.2.2
				7.6.100.0*	
				7.5.102.0****	
				7.4.150.0****	
				7.4.140.0****	
				7.4.130.0****	
				7.4.121.0****	
				7.4.110.0****	
				7.4.100.60****	
				7.4.100.0****	
				7.3.112.0****	
				7.3.101.0****	
				7.2.111.3****	
				7.2.110.0****	
				7.2.103.0****	
				7.0.240.0****	
				7.0.235.3****	
				7.0.235.0****	
				7.0.230.0****	
				7.1.91.0****	
				7.0.220.0****	
				7.0.116.0****	
				7.0.98.218****	
				7.0.98.0****	

MSE 3355	MSE 3365	MSE Virtual Appliance	Prime Infrastructure	Controller	Converged A
7.6.120.0	—	7.6.120.0	2.2.1 2.2 2.1.2 2.1.1** 2.1 2.0 1.4.2	7.6.120.0 7.6.110.0* 7.6.100.0* 7.5.102.0 7.4.150.0 7.4.140.0 7.4.130.0 7.4.121.0 7.4.110.0 7.4.100.60 7.4.100.0 7.3.112.0 7.3.101.0 7.2.111.3 7.2.110.0 7.2.103.0 7.0.240.0 7.0.235.3 7.0.235.0 7.0.230.0 7.1.91.0 7.0.220.0 7.0.116.0 7.0.98.218 7.0.98.0	—

MSE 3355	MSE 3365	MSE Virtual Appliance	Prime Infrastructure	Controller	Converge
7.6.132.0	—	7.6.132.0	2.2.1 2.2 2.1.2 2.1.1** 2.1 2.0 1.4.2	7.6.130.0 7.6.120.0 7.6.110.0* 7.6.100.0* 7.5.102.0 7.4.150.0 7.4.140.0 7.4.130.0 7.4.121.0 7.4.110.0 7.4.100.60 7.4.100.0 7.3.112.0 7.3.101.0 7.2.111.3 7.2.110.0 7.2.103.0 7.0.240.0 7.0.235.3 7.0.235.0 7.0.230.0 7.1.91.0 7.0.220.0 7.0.116.0 7.0.98.218 7.0.98.0	—

MSE 3355	MSE 3365	MSE Virtual Appliance	Prime Infrastructure	Controller	Converged A
7.6.100.0	—	7.6.100.0	2.2.1 2.2 2.1.2 2.1.1 2.1 2.0 Update 1 for 1.4.0.45* Update 2 for 1.4.0.45**	7.6.110.0* 7.6.100.0* 7.5.102.0 7.4.150.0 7.4.140.0 7.4.130.0 7.4.121.0 7.4.110.0 7.4.100.60 7.4.100.0 7.3.112.0 7.3.101.0 7.2.111.3 7.2.110.0 7.2.103.0 7.0.240.0 7.0.235.3 7.0.235.0 7.0.230.0 7.1.91.0 7.0.220.0 7.0.116.0 7.0.98.218 7.0.98.0	—

MSE 3355	MSE 3365	MSE Virtual Appliance	Prime Infrastructure	Controller	Converge
7.6.100.0	—	7.6.100.0	2.2.1	7.6.110.0**	3.2.2**
			2.2	7.6.100.0**	3.3.2**
			2.1.2	7.5.102.0**	
			2.1.1	7.4.150.0	
			2.1	7.4.140.0	
			2.0*	7.4.130.0	
				7.4.121.0	
				7.4.110.0	
				7.4.100.60	
				7.4.100.0	
				7.3.112.0	
				7.3.101.0	
				7.2.111.3	
				7.2.110.0	
				7.2.103.0	
				7.0.240.0	
				7.0.235.3	
				7.0.235.0	
				7.0.230.0	
				7.1.91.0	
				7.0.220.0	
				7.0.116.0	
				7.0.98.218	
				7.0.98.0	

MSE 3355	MSE 3365	MSE Virtual Appliance	Prime Infrastructure	Controller	Converged A
7.5.102.101	—	7.5.102.101	2.2.1 2.2 2.1.2 2.1.1 2.1 2.0 Update 1 for 1.4.0.45 1.4.0.45	7.5.102.0 7.4.150.0 7.4.140.0 7.4.130.0 7.4.121.0 7.4.110.0 7.4.100.60 7.4.100.0 7.3.112.0 7.3.101.0 7.2.111.3 7.2.110.0 7.2.103.0 7.0.240.0 7.0.235.3 7.0.235.0 7.0.230.0 7.1.91.0 7.0.220.0 7.0.116.0 7.0.98.218 7.0.98.0	—



MSE 3355	MSE 3365	MSE Virtual Appliance	Prime Infrastructure	Controller	Converge
7.5.102.101	—	7.5.102.101	2.2.1	7.5.102.0	3.2.2**
			2.2	7.4.150.0	3.3.2**
			2.1.2	7.4.140.0	
			2.1.1	7.4.130.0	
			2.1	7.4.121.0	
			2.0*	7.4.110.0	
				7.4.100.60	
				7.4.100.0	
				7.3.112.0	
				7.3.101.0	
				7.2.111.3	
				7.2.110.0	
				7.2.103.0	
				7.0.240.0	
				7.0.235.3	
				7.0.235.0	
				7.0.230.0	
				7.1.91.0	
				7.0.220.0	
				7.0.116.0	
				7.0.98.218	
				7.0.98.0	

## Cisco MSE Compatibility Matrix for Legacy Software Versions

Information in this section cites cross-platform compatibility testing performed from only the Cisco MSE perspective and is limited to up to specific product releases cited in this section.

For Cisco MSE compatibility with product releases not cited in this section, see the compatibility matrix for the relevant product. For example, for the most recent compatibility information between Cisco CMX and Cisco MSE, see the [Cisco CMX Compatibility Matrix, on page 74](#).

For Cisco MSE compatibility with Cisco Prime Infrastructure releases, see the applicable Cisco Prime Infrastructure release notes at:

<https://www.cisco.com/c/en/us/support/cloud-systems-management/prime-infrastructure/products-release-notes-list.html>

Table 16: Cisco MSE Compatibility Matrix—Legacy Software Versions

MSE 3355	MSE 3350	MSE Virtual Appliance	AeroScout CLE	WCS	Controller
7.4.121.0	—	7.4.121.0	4.5.2.16 4.4.2.11	—	7.4.150.0 7.4.140.0 7.4.130.0 7.4.121.0 7.4.110.0 7.4.100.60 7.4.100.0 7.3.112.0 7.3.101.0 7.2.111.3 7.2.110.0 7.2.103.0 7.0.240.0 7.0.235.3 7.0.235.0 7.0.230.0 7.1.91.0 7.0.220.0 7.0.116.0 7.0.98.218 7.0.98.0

MSE 3355	MSE 3350	MSE Virtual Appliance	AeroScout CLE	WCS	Controlle
7.4.110.0	—	7.4.110.0	4.4.2.11	—	7.4.110.0 7.4.100.6 7.4.100.0 7.3.112.0 7.3.101.0 7.2.111.3 7.2.110.0 7.2.103.0 7.0.240.0 7.0.235.3 7.0.235.0 7.0.230.0 7.1.91.0 7.0.220.0 7.0.116.0 7.0.98.21 7.0.98.0
7.4.100.0	—	7.4.100.0	4.4.2.114.4.2.7	—	7.4.100.0 7.3.112.0 7.3.101.0 7.2.111.3 7.2.110.0 7.2.103.0 7.0.240.0 7.0.235.3 7.0.235.0 7.0.230.0 7.1.91.0 7.0.220.0 7.0.116.0 7.0.98.21 7.0.98.0

MSE 3355	MSE 3350	MSE Virtual Appliance	AeroScout CLE	WCS	Controller
7.3.101.0	7.3.101.0	7.3.101.0	4.4.2.4	—	7.4.150.0 7.4.140.0 7.4.130.0 7.4.121.0 7.4.110.0 7.4.100.60 7.4.100.0 7.2.111.3 7.2.110.0 7.2.103.0 7.0.240.0 7.0.235.3 7.0.235.0 7.0.230.0 7.1.91.0 7.0.220.0 7.0.116.0 7.0.98.218 7.0.98.0
7.2.110.0	7.2.110.0	7.2.110.0	4.4.2.4	—	7.2.111.3 7.2.110.0 7.2.103.0 7.0.240.0 7.0.235.3 7.0.235.0 7.0.230.0 7.1.91.0 7.0.220.0 7.0.116.0 7.0.98.218 7.0.98.0

<b>MSE 3355</b>	<b>MSE 3350</b>	<b>MSE Virtual Appliance</b>	<b>AeroScout CLE</b>	<b>WCS</b>	<b>Controlle</b>
7.2.103.0	7.2.103.0	7.2.103.0	4.4.1.4	—	7.2.103.0 7.0.240.0 7.0.235.3 7.0.235.0 7.0.230.0 7.1.91.0 7.0.220.0 7.0.116.0 7.0.98.21 7.0.98.0
7.0.240.0	7.0.240.0	—	4.3.1.10	7.0.240.0	7.0.240.0 7.0.235.3 7.0.235.0 7.0.230.0 7.1.91.0 7.0.220.0 7.0.116.0 7.0.98.21 7.0.98.0
7.0.230.0	7.0.230.0	—	4.3.1.19	7.0.230.0	7.0.235.3 7.0.235.0 7.0.230.0 7.1.91.0 7.0.220.0 7.0.116.0 7.0.98.21 7.0.98.0

<b>MSE 3355</b>	<b>MSE 3350</b>	<b>MSE Virtual Appliance</b>	<b>AeroScout CLE</b>	<b>WCS</b>	<b>Controller</b>
7.0.220.0	7.0.220.0	—	4.3.1.19	7.0.220.0	7.1.91.0 7.0.220.0 7.0.116.0 7.0.98.218 7.0.98.0
7.0.201.204	7.0.201.204	—	4.2.4.4	7.0.172.0	7.0.116.0 7.0.98.218 7.0.98.0
7.0.112.0	7.0.112.0	—	4.2.4.4	7.0.164.3 7.0.164.0	7.0.98.218 7.0.98.0

MSE 3355	MSE 3350	MSE Virtual Appliance	AeroScout CLE	WCS	Controller
7.0.105.0	7.0.105.0	—	4.2.4.4	7.0.164.3	7.0.98.2

## Cisco Mobility Express Solution Compatibility Matrix

This section contains compatibility information about the Cisco Mobility Express Solution.



---

**Note** The Cisco Mobility Express solution is not compatible with other Cisco Wireless LAN Controller deployments and Cisco Network Assistant.

---

Table 17: Mobility Express Software Compatibility Matrix

Cisco Mobility Express Solution	Access Point Software	Access Point Platforms	Cisco CMX	Cisco ISE	Cisco P structur
8.10.185.0	15.3(3)JK9	APs with integrated controller functionality:  Cisco Aironet 1540 series, 1560 series, 1815i, 1815m, 1815w, 1830 series, 1850 series, 2800 series, 3800 series, 4800 series, Cisco 6300 Series Embedded Services, and Cisco Catalyst IW6300 Heavy Duty Series	10.6.3-70	2.8	3.9.1
8.10.183.0	15.3(3)JK8b			2.7	3.9
8.10.182.0	15.3(3)JK8a			3.8.1	
8.10.181.0	15.3(3)JK8			3.8	
8.10.171.0	15.3(3)JK7				
8.10.162.0	15.3(3)JK6				
8.10.151.0	15.3(3)JK5			APs without integrated controller functionality:	10.6.3-70
8.10.142.0	15.3(3)JK4	Cisco Aironet 700i, 700w, 1700 series, 1810i, 1810w, 2700 series, 3700 series, Industrial Wireless 3702, Cisco Catalyst 9100	10.6.3-70	2.6	3.8.1
8.10.130.0	15.3(3)JK3		2.4	3.8	
			2.3		
			2.2		
				2.1	
8.10.122.0	15.3(3)JK2a	APs with integrated controller functionality:  Cisco Aironet 1540 series, 1560 series, 1815i, 1815m, 1815w, 1830 series, 1850 series, 2800 series, 3800 series, 4800 series, Cisco 6300 Series Embedded Services, and Cisco Catalyst IW6300 Heavy Duty Series	10.6.3-70	2.6	3.7
8.10.121.0	15.3(3)JK2			2.4	
8.10.113.0	15.3(3)JK1t			2.3	
8.10.112.0	15.3(3)JK1			2.2	
8.10.105.0	15.3(3)JK			2.1	
		APs without integrated controller functionality:  Cisco Aironet 700i, 700w, 1700 series, 1810i, 1810w, 2700 series, 3700 series, Industrial Wireless 3702, Cisco Catalyst 9100			



Cisco Mobility Express Solution	Access Point Software	Access Point Platforms	Cisco CMX	Cisco ISE	Cisco ISE
8.9.111.0 8.9.100.0	15.3(3)JJ1 15.3(3)JJ	<p>APs with integrated controller functionality:</p> <p>Cisco Aironet 1540 series, 1560 series, 1815i, 1815m, 1815w, 1830 series, 1850 series, 2800 series, 3800 series, and 4800 series.*</p> <p>APs without integrated controller functionality:</p> <p>Cisco Aironet 700i, 700w, 1700 series, 1810i, 1810w, 2700 series, 3700 series, Industrial Wireless 3702, Cisco Catalyst 9100 (with Release 8.9.111.0)</p>	10.2.2 and later	2.6 2.4 2.3 2.2 2.1	3.7 3.6
8.8.130.0 8.8.125.0 8.8.120.0 8.8.111.0 8.8.100.0	15.3(3)JI6 15.3(3)JI5 15.3(3)JI4 15.3(3)JI3 15.3(3)JI1	<p>APs with integrated controller functionality:</p> <p>Cisco Aironet 1540 series, 1560 series, 1815i, 1815m, 1815w, 1830 series, 1850 series, 2800 series, 3800 series, and 4800 series.*</p> <p>APs without integrated controller functionality:</p> <p>Cisco Aironet 700i, 700w, 1700 series, 1810w, 2700 series, 3700 series</p>	10.2.2 and later	2.2 2.1	3.5 3.4 3.3 3.2 3.1. 3.1.
8.7.102.0	15.3(3)JH	<p>APs with integrated controller functionality:</p> <p>Cisco Aironet 1540 series, 1560 series, 1815i, 1815m, 1815w, 1830 series, 1850 series, 2800 series, and 3800 series.*</p> <p>APs without integrated controller functionality:</p> <p>Cisco Aironet 700i, 700w, 1700 series, 1810w, 2700 series, 3700 series</p>	10.2.2 and later	2.2 2.1	3.4 3.3 3.2 3.1. 3.1.

Cisco Mobility Express Solution	Access Point Software	Access Point Platforms	Cisco CMX	Cisco ISE	Cisco P structur
8.6.101.0	15.3(3)JG1	<p>APs with integrated controller functionality:</p> <p>Cisco Aironet 1540 series, 1560 series, 1815i, 1815m, 1815w, 1830 series, 1850 series, 2800 series, and 3800 series.*</p> <p>APs without integrated controller functionality:</p> <p>Cisco Aironet 700i, 700w, 1700 series, 1810w, 2700 series, 3700 series</p>	10.2.2 and later	2.2 2.1	3.4 3.3 3.2 3.1.6 3.1.5
8.5.182.0	15.3(3)JF15	<p>APs with integrated controller functionality:</p> <p>Cisco Aironet 1540 series, 1560 series, 1815i, 1815m, 1815w, 1830 series, 1850 series, 2800 series, and 3800 series.*</p> <p>APs without integrated controller functionality:</p> <p>Cisco Aironet 700i, 700w, 1600 series, 1700 series, 1810w series, 2600 series, 2700 series, 3500 series, 3600 series, 3700 series</p>	10.2.2 and later	2.2 2.1	3.9.1
8.5.17x.0	15.3(3)JF14				3.9
8.5.16x.0	15.3(3)JF12i				3.8.1
	15.3(3)JF12				3.8
	15.3(3)JF11				3.7.1
8.5.151.0	15.3(3)JF10				3.7
8.5.140.0	15.3(3)JF9				3.6
8.5.13x.0	15.3(3)JF8				3.5
	15.3(3)JF7				
8.5.120.0	15.3(3)JF5				
8.5.110.0	15.3(3)JF4				
8.5.10x.0	15.3(3)JF1				
	15.3(3)JF				

Cisco Mobility Express Solution	Access Point Software	Access Point Platforms	Cisco CMX	Cisco ISE	Cisco stru
8.4.100.0	15.3(3)JE	<p>APs with integrated controller functionality:</p> <p>Cisco Aironet 1560 series, 1815i, 1815w, 1830 series, 1850 series, 2800 series, and 3800 series.*</p> <p>APs without integrated controller functionality:</p> <p>Cisco Aironet 700i, 700w, 1600 series, 1700 series, 1810w series, 2600 series, 2700 series, 3500 series, 3600 series, 3700 series</p>	10.2.2 and later	2.2 2.1	3.2 3.1. 3.1.
8.3.130.0	15.3(3)JD7, 15.3(3)JDA7	<p>APs with integrated controller functionality:</p> <ul style="list-style-type: none"> <li>• Cisco Aironet 1560, 1830, 1850, 2800, and 3800 series</li> </ul>	—	—	3.2 3.1.
8.3.122.0	15.3(3)JD6	<p>APs without integrated controller functionality:</p> <ul style="list-style-type: none"> <li>• Cisco Aironet 700i, 700w, 1600 series, 1700 series, 1810w series, 2600 series, 2700 series, 3500 series, 3600 series, 3700 series</li> </ul>	—	—	3.1.
8.3.121.0	15.3(3)JD5				
8.3.112.0	15.3(3)JD4				
8.3.102.0	15.3(3)JD	<p>APs with integrated controller functionality:</p> <ul style="list-style-type: none"> <li>• Cisco Aironet 1830, 1850, 2800, and 3800 series</li> </ul> <p>APs without integrated controller functionality:</p> <ul style="list-style-type: none"> <li>• Cisco Aironet 700i, 700w, 1600 series, 1700 series, 1810w series, 2600 series, 2700 series, 3500 series, 3600 series, 3700 series</li> </ul>	—	—	3.2 3.1. 3.1. 3.1.

Cisco Mobility Express Solution	Access Point Software	Access Point Platforms	Cisco CMX	Cisco ISE	Cisco P structur
8.2.100.0	15.3(3)JC	APs with integrated controller functionality: <ul style="list-style-type: none"> <li>• Cisco Aironet 1850 series, 1830 series</li> </ul> APs without integrated controller functionality: <ul style="list-style-type: none"> <li>• Cisco Aironet 700i, 700w, 1600 series, 1700 series, 2600 series, 2700 series, 3500 series, 3600 series, 3700 series</li> </ul>	—	1.4	1.4
8.1.122.0	15.3(3)JBB5				1.3

## Cisco Support Community

Cisco Support Community is a forum for you to ask and answer questions, share suggestions, and collaborate with your peers. Join the forum at: <https://supportforums.cisco.com/index.jspa>.

## Communications, Services, and Additional Information

- To receive timely, relevant information from Cisco, sign up at [Cisco Profile Manager](#).
- To get the business impact you're looking for with the technologies that matter, visit [Cisco Services](#).
- To submit a service request, visit [Cisco Support](#).
- To discover and browse secure, validated enterprise-class apps, products, solutions, and services, visit [Cisco DevNet](#).
- To obtain general networking, training, and certification titles, visit [Cisco Press](#).
- To find warranty information for a specific product or product family, access [Cisco Warranty Finder](#).

## Cisco Bug Search Tool

[Cisco Bug Search Tool](#) (BST) is a gateway to the Cisco bug-tracking system, which maintains a comprehensive list of defects and vulnerabilities in Cisco products and software. The BST provides you with detailed defect information about your products and software.

## Documentation Feedback

To provide feedback about Cisco technical documentation, use the feedback form available in the right pane of every online document.

---

The documentation set for this product strives to use bias-free language. For purposes of this documentation set, bias-free is defined as language that does not imply discrimination based on age, disability, gender, racial identity, ethnic identity, sexual orientation, socioeconomic status, and intersectionality. Exceptions may be present in the documentation due to language that is hardcoded in the user interfaces of the product software, language used based on standards documentation, or language that is used by a referenced third-party product.

Cisco and the Cisco logo are trademarks or registered trademarks of Cisco and/or its affiliates in the U.S. and other countries. To view a list of Cisco trademarks, go to this URL: <https://www.cisco.com/c/en/us/about/legal/trademarks.html>. Third-party trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1721R)

© 2017–2023 Cisco Systems, Inc. All rights reserved.